


INSTALLATION AND WIRING DIAGRAM

INDIVIDUAL LIGHTS

RAINBOW II 4" CEILING MOUNT

ART. NO.	131 725bz/CM	bronze, orange glass	131 729bz/CM	bronze, red glass	131 916bz/CM	bronze, rainbow glass
	131 725ch/CM	chrome, orange glass	131 729ch/CM	chrome, red glass	131 916ch/CM	chrome, rainbow glass
	131 725mc/CM	matte chrome, orange glass	131 729mc/CM	matte chrome, red glass	131 916mc/CM	matte chrome, rainbow glass
	131 726bz/CM	bronze, smoke glass	131 816bz/CM	bronze, retro white glass	131 919bz/CM	bronze, sunrise glass
	131 726ch/CM	chrome, smoke glass	131 816ch/CM	chrome, retro white glass	131 919ch/CM	chrome, sunrise glass
	131 726mc/CM	matte chrome, smoke glass	131 816mc/CM	matte chrome, retro white glass	131 919mc/CM	matte chrome, sunrise glass
	131 728bz/CM	bronze, turquoise glass	131 817bz/CM	bronze, retro black glass		
	131 728ch/CM	chrome, turquoise glass	131 817ch/CM	chrome, retro black glass		
	131 728mc/CM	matte chrome, turquoise glass	131 817mc/CM	matte chrome, retro black glass		



IMPORTANT SAFETY INSTRUCTIONS



1. Read all instructions!
2. Turn off power prior to any work on the systems.
3. Only a qualified electrician should install this hard wired transformer.
4. For all the wire connections, use UL listed Wire Nuts.
5. Only BRUCK fixtures and components may be used with the system.
6. Only BRUCK fixtures and components may be used with the system.
7. Total wattage of the system must never exceed the wattage supplied by the low voltage transformer.
8. Please check that the total lamp wattage does not exceed 50W per circuit or wattage specified by fixture.
9. Secondary connections must be clean and tight to avoid arcing and overheating!
10. Warranty is void in case of unauthorized modifications and/ or improper use.

READ ALL OF THESE INSTALLATION INSTRUCTIONS BEFORE INSTALLING THE FIXTURE

Contents of Delivery:

RAINBOW II 4" CEILING MOUNT - qty. (1)

Step 1.

- The Rainbow II CM can be mounted directly to any wall with access to the power cables.

- Begin by connecting the two wires from the transformer (A) to the power cables in the wall. Then slide the notched plastic washer (B) through the mounting screw (C). Insert the screw (C) into the mounting plate (D) and slide the plastic washer (E) onto the end of the screw. Align the screws (C) with the J-box and tighten until firmly connected.

- Connect quick connect (I) then place the canopy cover (F) over the mounting plate (D) and secure it with the allen screw (G) located on the side of the base.

- Turn glass shade (H) clockwise to complete fixture installation.

