

Instructions: LEDme Button Light Class II Dimmable Drivers

CAUTION –To reduce the risk of fire, electric shock or injury to persons:

- Always turn off power at main switch prior to installation.
- System intended for installation by a qualified electrician, in accordance with NEC and local regulations. Consult with local inspector to assure compliance.
- For use with LED loads.

Model	LED-350MA09-DIM-RB	LED-350MA12-DIM-RB
Input Voltage	120Vac,60Hz	120Vac,60Hz
Input Current	Max 0.15A	Max 0.2A
Output Current	350mA	350mA
Each Port Output Voltage	2-12V DC	2-12V DC
Each Port Load	3x1W LED Light or 1-3PCS LED	3x1W LED Light or 1-3PCS LED
Each Port Load Lead Wires	12-22AWG	12-22AWG
Output Port	3 PCS	4 PCS

FEATURES:

- 350mA Constant Current for LED's optimized and stable performance.
- Capable of supplying power to a single LED fixture, or more LED fixtures at once.
- Special circuit design to output open circuit protection.
- Input may used reverse phase dimmer to LED driver dimmable.

INSTALLATION:

1. Loosen two cover screws and remove the cover. Inside there four separate sets of wiring terminals.
2. Push down one set of the wiring terminals and insert fixture's red wire into the "+" terminal and the black wire into the "-" terminal.
3. LED used series connection.
4. After connecting all the LED fixtures, secure the cover by tightening the two screws.
5. The product should be installed on the either internal or external surface of any indoor construction.

MOUNTING INSTRUCTIONS

