

Z15 LED Canopy Spot



**READ AND FOLLOW ALL WARNINGS AND INSTRUCTIONS BEFORE INSTALLING OR MAINTAINING THIS PRODUCT.
TURN OFF POWER PRIOR TO ANY WORK ON THE SYSTEM OR PRODUCT.
DO NOT INSTALL DAMAGED PRODUCT.**

Installing, wiring, and maintenance must be done by qualified persons or a certified electrician in accordance with all local and National Electrical Codes.

Warranty is voided in case of unauthorized modifications and/or improper use.

Save these instructions. Use as reference when service or maintenance is performed.

CAUTION – Do not install any fixture assembly closer than 6 inches (15.24 cm) from any combustible material.

Suitable for dry locations only.

⚠ WARNING ⚠

- To avoid possible electrical shock, before installing light fixtures, disconnect power by turning off the circuit breakers both to the outlet box and to its associated wall switch location if you cannot lock the circuit breakers in the off position, securely fasten a prominent warning device, such as a tag to the service panel.
- Verify that supply voltage is correct by comparing it with the luminaire label information.
- Make all electrical and grounded connections in the accordance with the National Electrical Code (NEC) and any applicable local code requirements.
- Allow sufficient time for fixture and / or driver to cool before servicing and performing maintenance.

⚠ CAUTION ⚠

- All wiring must be in accordance with national and local electrical codes and ANSI/NFPA 70. If you are unfamiliar with wiring you should use qualified electrician.
- PPE Personal Protective Equipment such as gloves and safety glasses should be used at all times when installing, maintaining or servicing.
- Risk of fire. Keep combustible material away from fixtures.

⚠ ADVERTENCIA ⚠

- Para evitar un posible choque, antes de instalar luminarias, desconecte la alimentación apagando los interruptores de circuito y ubicación del interruptor de pared. Si no se pueden bloquear los interruptores en la posición de apagado, sujetar un dispositivo de advertencia en el panel de servicio.
- Compruebe que la tensión de alimentación es correcta comparándola con la información de etiqueta de la luminaria.
- Hacer todas las conexiones eléctricas y puesta a tierra de acuerdo con el código eléctrico nacional (NEC) y los requisitos del código local aplicable.
- Permitir suficiente tiempo para el luminario y el controlador para enfriar antes de enpesar el servicios y mantenimiento.

⚠ PRECAUCION ⚠

- Todo el cableado debe hacerse de conformidad con los códigos eléctricos nacionales y locales y ANSI/NFPA 70. Si no está familiarizado con el cableado, se debe utilizar a un electricista.
- Equipo de protección personal como guantes y lentes de seguridad se debe utilizar al instalar, mantener o reparar.
- Riesgo de incendio. Mantenga los materiales combustibles lejos de los liminario.

⚠ AVERTISSEMENT ⚠


- Pour éviter les chocs, avant d'installer des appareils d'éclairage, coupez l'alimentation en désactivant les disjoncteurs et l'emplacement du commutateur mural. Si vous ne pouvez pas verrouiller les disjoncteurs en position d'arrêt, fixer un avertissement sur le panneau de service.
- Vérifiez que la tension d'alimentation est correcte en le comparant avec les informations d'étiquette de luminaire.
- Effectuer tous les raccordements électriques et mise à la terre dans la conformité avec le Code électrique National (NEC) et des exigences du code local applicable.
- Laisser suffisamment de temps pour l'appareil et pilote refroidir avant d'effectuer l'entretien et la maintenance.

⚠ MIS EN GARDE ⚠

- Tout le câblage doit être effectué conformément aux codes électriques locaux et nationaux et ANSI/NFPA 70. Si vous êtes peu familier avec câblage, vous devez utiliser un électricien qualifié.
- Équipement de protection personnelle comme des gants et des lunettes de sécurité doivent être utilisé en tout temps lors de l'installation, maintenance ou entretien.
- Risque d'incendie. Garder les matières combustibles loin de luminaires.

INSTRUCTIONS FOR USE

- 1 De-energize circuit before installation.
- 2 Use 1.5mm allen key to remove back plate assembly.
- 3 Secure back plate assembly to a J-Box (J-Box and mounting hardware supplied by others) for use with 3-1/2" and 4" octagonal or square recessed junction boxes with 2-3/4" mounting hole spacing. (Appropriate device ring cover may be required and to be supplied by others.)
- 4 *For fixtures with rigid stems longer than 5 inches only. Feed fixture wiring through threaded end of rigid stem and thread stem on to swivel adapter. Slide bottom locking ring over wiring and rigid stem. Align hole at base of rigid stem with hole on bottom locking ring and tighten set screw. Insert wiring and rigid stem into canopy. Set top locking ring flush with top of rigid stem, align holes, and tighten safety screw. Raise canopy to until rigid stem is fully seated. Tighten (3) stem locking screws on mounting flange at base of canopy.
- 5 Properly ground back plate assembly and canopy in accordance with all local and national electrical codes.
- 6 Connect line, neutral, and ground wires to building electrical supply. If product supports optional dimming, connect dimming leads to dimming control system (provided by others) or isolate wires individually. Refer to product cut sheet for input voltage requirements.
- 7 Secure canopy to back plate assembly using 1.5mm allen key and place fixture into desired position.
- 8 Energize circuit and test for proper operation



FIELD CUT RIGID STEM

- 1 De-energize circuit before removing fixture.
- 2 Remove fixture from back plate using 1.5mm allen key. Remove top locking ring. Use 1.5mm allen key to loosen set screw.
- 3 Use 2.5mm allen key to loosen (3) three stem locking set screws on canopy mounting flange to separate rigid stem from canopy.
- 4 Loosen set screw on bottom locking ring and unscrew rigid stem to separate from fixture.
- 5 Field cut only after removed from canopy and wiring has been removed from stem. Cut the stem to desired length and deburr the inside edge.
- 6 Drill 1/8 inch hole into top of stem. Hole must be drilled 1/8 inch from the cut end for the safety set screw. Remove any sharp edges.
- 7 Feed fixture wiring through threaded side of rigid stem. Thread stem into swivel adapter and slide bottom locking ring into position. Align with hole on rigid stem and tighten bottom locking ring set screw.
- 8 Feed rigid stem through canopy, insert top locking ring into position, align hole, and tighten set screw. Raise canopy until top locking ring is fully seated on canopy. Tighten (3) three stem locking screws on canopy mounting flange.
- 9 Properly ground back plate assembly and canopy in accordance with all local and national electrical codes.
- 10 Connect line, neutral, and ground wires to building electrical supply. If product supports optional dimming, connect dimming leads to dimming control system (provided by others) or isolate wires individually. Refer to product cut sheet for input voltage requirements.
- 11 Secure canopy to back plate assembly using 1.5mm allen key and place fixture into desired position.
- 12 Energize circuit and test for proper operation.

