

INFINEX

**DIMMER
MOTION SENSOR + DIMMER**



Dimmer Only

Touch On/Off Gradual dimming from 100%-5%
Power failure memory (retains last setting)
10 hour automatic energy saving shutoff

Dimmer + Motion Combo

4 step dimming 100/75/50/25
30S/3MIN/30MIN preset motion sensor
Motion sensor can be deactivated
Dimmer works in motion sensor mode or standalone mode
10 hour automatic energy saving shutoff in dimmer only mode

INPUT: 12V/24VDC

OUTPUT (MAX): 12VDC 60W, 24VDC 96W (use included barrel adaptors for 24VDC operation)

OPERATION

Dimmer Only Unit

Tap green sensor once for on/off.

Hold finger down to dim gradually or to raise intensity level. Light will blink once highest or lowest level intensity has been reached.

Light will automatically turn off after 10 hours of non-interrupted use (i.e dimmer has not been touched in 10 hours).

Dimmer + Combo Unit

(note: unit is preset from factory to motion sensor mode)

Hold finger down on green sensor. When lights flash once; the motion sensor has been turned off. Hold finger down again, when lights flash 3 times the motion sensor is turned back on.

Light will turn off after X minutes in motion sensor mode (time varies with model) if no motion is detected.

Dimmer function works in both motion sensor on or off mode. Single tap finger on sensor for 4-step dimming plus off.

Light will automatically turn off after 10 hours of non-interrupted use (i.e dimmer has not been touched in 10 hours).