

NON-ENCLOSED ELECTRONIC

Transformers

WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project:

Location:

PRODUCT DESCRIPTION

Low Voltage electronic transformer designed to be used as a replacement part for factory installed transformers. Transformer may be safely loaded to 100% of stated capacity.

FEATURES

- 1W minimum load
- All connections must be made in an enclosure for proper installations
- Dimmable with electronic low voltage dimmers. Dimmers should always be installed on the primary side of the transformer.

SPECIFICATIONS

Construction: Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp.

Output: 12V, 24V

Frequency: 20khz

Details: In the case of a system overload or short circuit the transformer will revert to a "hold" position and then automatically reset the system when the problem is solved. System protection is designed to last several hours.

Standards: UL ready components

ORDER NUMBER

Model	Output	L	W	H
EN-12100-R-AR	12V, 100W	3½"	1½"	1¼"
EN-12150-R-AR	12V, 150W	3½"	1½"	1¼"
EN-24150-R-AR	24V, 150W	3½"	1½"	1¼"

EN - - R-AR

Example: EN-24150-R-AR

ACCESSORIES

Multiple Terminal Block

Accommodates up to 6 output connections for 14 AWG wires. Terminal block is used to easily wire together multiple output connections for a neat under cabinet installation without the use of open splices. Perfect for wiring up to 3 button lights at 20W or 6 button lights at 10W.

Model	L	W	H
MTB-01	3¼"	1¾"	7⁄8"

WAC Lighting

www.waclighting.com

Phone (800) 526.2588 • Fax (800) 526.2585

Headquarters/Eastern Distribution Center

44 Harbor Park Drive • Port Washington, NY 11050

Phone (516) 515.5000 • Fax (516) 515.5050

Western Distribution Center

1750 Archibald Avenue • Ontario, CA 91760

Phone (800) 526.2588 • Fax (800) 526.2585