



Job Name:

Contact:

Fixture Type:

Part Number:

### T-300 REMOTE TRANSFORMER



#### Description:

The T-300 series magnetic remote transformer features a metal enclosure with a covered wiring compartment. The additional boost tap output can be used to counter voltage drop due to longer powerfeeds. The core and coil are encapsulated for reliability and quiet operation. Please contact manufacturer for further details.

#### Part Numbers:

**T-300/120v** black, 300VA, 120v

**T-300/277v** black, 300VA, 277v

#### Technical Specs:

Transformer must be installed in a well ventilated location to allow heat dissipation.

300VA maximum

120V AC, 60Hz input & 277V AC, 60 Hz input

12V/12.6V(boost tap) AC output

Auto thermo shutoff (resettable) on primary

25A switch circuit breaker on secondary

5 x ?" electrical connect knockouts

