

LED FLUSH MOUNT




NEED HELP?
Call or Email us first

Our service team is ready to answer your questions...
1-800-265-1833 (English) / 1-800-567-2513 (French)
IN CANADA - resalescanada@canarmna.ca - IN USA - resalesusa@canarmna.ca

Monday – Friday
8 AM - 5 PM EST.



TOOLS AND MATERIALS REQUIRED:



Wiring supplies as required by local electrical code

WARNING:

1. READ ALL INSTRUCTION BEFORE INSTALLATION.
2. SYSTEM IS INTENDED FOR INSTALLATION BY A QUALIFIED ELECTRICIAN IN ACCORDANCE WITH THE NATIONAL ELECTRICAL CODE AND LOCAL REGULATIONS.
3. GO TO THE MAIN FUSE BOX, OR CIRCUIT BREAKER. PLACE THE MAIN POWER SWITCH IN THE "OFF" POSITION AND UNSCREW THE FUSE(S) OR SWITCH "OFF" THE CIRCUIT BREAKER SWITCH(ES) THAT CONTROL THE POWER TO THE FIXTURE OR ROOM THAT YOU ARE WORKING ON.
4. PLACE THE WALL SWITCH IN THE "OFF" POSITION.
5. SUPPLY CONDUCTORS (POWER WIRES) CONNECTING THE FIXTURE MUST BE RATED MINIMUM 90°C. IF UNCERTAIN, CONSULT AN ELECTRICIAN.

CAUTIONS:

1. THESE LUMINAIRES (FIXTURES) ARE DESIGNED TO MEET THE LATEST NEC REQUIREMENTS AND ARE LISTED IN FULL COMPLIANCE WITH ETL LIST.
2. BEFORE ATTEMPTING INSTALLATION, CHECK YOUR LOCAL ELECTRICAL CODE, AS IT SETS THE WIRING STANDARDS FOR YOUR LOCALITY.

INSTALLATION

1. Hold the supply wires and separate the fixture and lens.
2. Secure the mounting screws (only screwing on halfway) to electrical box.
3. Connect supply wires to fixture wires and insulate with proper size wire nuts. Connect incoming ground wire (green or bare) to fixture ground wire (green or bare). Connect incoming common (white) wire to fixture white wire. Connect incoming hot (typically black) wire to fixture black wire.
4. Once the wires are connected, ensure to push back all the wire nuts into the junction box.
5. Attach the fixture to the mounting screws, twist the fixture and tighten the screws. Secure the three wood screws with plastic anchors.
6. Put the label with red arrow beside the hole of the fixture on the ceiling. (Be sure the red arrow on the fixture and the arrow on the ceiling lined up properly.)
7. Select the CCT needed, 3000K/4000K/5000K for selection.
8. Twist and secure the lens.

Compatible wall dimmers : Leviton # 742-66EV-P0W, 742-6672-HLW, 722-6674-PDW, Lutron # SCL-153PH-WH

CL-19-13: Max # of Lamps per 150W Dimmer: 6 pcs
CL-19-20: Max # of Lamps per 150W Dimmer: 3 pcs

