

## Lighting Your Life Since 1970

Product Specifications - 8/906MB					
Job Name:		Job Type:			
Quantity:		Comments			
1					



## 87906MB

## CounterMax MX-L 30" LED Under Cabinet Light

Uses MXInterLink2 accessories. Click here for a complete list of compatible accessories.

Finish	Glass/Shade	<b>Product Category</b>
Metallic Bronze		Under Cabinet Kit

Lamping		Measurements		Shipping	
Number of Bulbs	6	Width	2.0"	Carton Weight	1.5 lbs
Light Type	LED	Height	1.0"	Carton Width	3"
Bulb Type	LED	Length	30.0"	Carton Height	2"
Max Bulb Wattage	1	Extension	N/A	Carton Length	36"
Max Fixture Wattage	6	Back Plate Width	N/A	Carton Cubic Feet	0.16
Rated Life	±50,000 Hours	Back Plate Height	N/A	Master Pack	6
Rated Lumens	±480	HCO	N/A	Master Pack Weight	11.5 lbs
Color Temp	±3,000 K	Min Overall Height	N/A	Master Pack Width	7.9"
Bulb(s)	Integrated	Max Overall Height	N/A	Master Pack Height	7.8"
Light Up/Down	N/A	Hanging Weight	1.5 lbs	Master Pack Length	36.9"
Beam Spread	120	Height Adjustable	N/A	Master Cubic Feet	1.30
CRI	78-80	Slope	N/A	UPS Shippable	Yes
Photo Cell Included	N/A	Chain Length	N/A		
Ballast/Driver/Transformer	No	Wire Length	N/A		
Dimmable	No	Canopy Width	N/A		
		Canopy Height	N/A		
		Canopy Length	N/A		

Certification		Other		Equivalents	
Safety Rating	Dry	UPC Code	783209064546	Incandescent Watts	43.64
Energy Star	No	Shades Included	N/A	Fluorescent Watts	9.6
CA Title 24	No	Crystals Included	N/A		
CA Title 20	No	Diffuser Included	N/A		
ADA	No	Conversion Kit	N/A		
Dark Sky	N/A	Material	Aluminum		

Maxim Lighting International and all designs, logos and images © 2013 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.