# HR-LED87

## LEDme® Button Light

## WAC LIGHTING

Responsible Lighting®

	Surface Mount $\frac{1}{76''} = 214'' 1$	Fixture Type:
	Recessed Mount $ \frac{1}{5\%''} \left( \begin{array}{c} 1\%'' \\ 1\%'' \\ 1 \end{array} \right) $	Project: Location:

SPECIFICATIONS

**Construction:** Die-cast aluminum fixture, stamped steel housing

Wiring: Includes 72" pre-installed wires that lead out through the top.

20 button lights to be wired together. Use a multiple terminal block to wire up to 6 fixtures in a neat under cabinet installation without the

**Mounting:** *Recessed*- 2<sup>1</sup>/<sub>8</sub>" cutout hole. Compression springs hold fixture firmly in place. *Surface*- Screw housing cover to surface,

Brushed Nickel (BN), Copper Bronze (CB) and Chrome (CH).

Transformers: Class 2, 24V remote and plug-in transformers allow for up to

Dimming: May be dimmed to 10% with an electronic low voltage (ELV) dimmer.

compress springs and insert into cover. Not recommended for use in ceiling.

Finish: Black (BK), Dark Bronze (DB) and White (WT) powder coat, electroplated

for surface mount. Glass beam spread lens.

use of open splices (see below).

Light Source: Six 3000K LEDs.

Standards: UL & CUL Listed.

## PRODUCT DESCRIPTION

Designed for recessed or surface mounted installations, delivering strong light output with the latest in LED technology.

## FEATURES

- Recessed or surface mounting
- Quick and easy installation
- Includes 72" lead wire
- Replaceable LED module
- 3000K color temperature
- 50,000 hour rated life
- UL and CUL Listed

**ORDER NUMBER** 

Model #

HR-LED87

HR-LED87S

• 5 year WAC Lighting product warranty

## **FIXTURE PERFORMANCE**

	Watt	Lumens	Efficacy	CRI
HR-LED87	4.8 W	180	38 Lm/W	05
HR-LED87S	4.8 W	156	33 Lm/W	85

Finish **BK** 

BN

СВ

СН

DB WT Black


Chrome

White

**Brushed Nickel** 

Copper Bronze

Dark Bronze



## REPLACEMENT MODULE

	Color Temp
RM3X1-30-HR	3000K

## **RETROFIT RECESSED HOUSING**

Model #	Finish
HR-LED-COV	BK, BN, CB, CH, DB, WT
	voltage HB-88 and HB-86

Use to replace low voltage HR-88 and HR-86 button lights using existing wiring and cutout.

#### Example: HR-LED87-BN

HR-LED87

## **CLASS 2 ELECTRONIC TRANSFORMERS**

Round

Square

Туре	Model	Dim	Input	Output	Power Up To	Dimensions
Domoto	EN-2460-RB2	Vac	120V	24V AC/60W	12 × LED87	c1/ ".v. 15/ ".v. 11/"
Remote	EN-24100-RB2	Yes	1200	24V AC/96W	20 × LED87	6½"×1%"×1¼"
Plug-In	EN-2460-P-AR	Yes	120V	24V AC/60W	12 × LED87	53%"×2½"×15%"

Includes 6' cord and 5 SL-WC-1 clips.

## MULTIPLE TERMINAL BLOCK

Model #	Dimens	sions	
MTB-01	L: 3¼"	W: 1¾"	H: %"

12.5A max accommodates up to 6 output connections for 14 AWG wires.

## WAC Lighting

www.waclighting.com Phone (800) 526.2588 • Fax (800) 526.2585 Headquarters/Eastern Distribution Center 44 Harbor Park Drive • Port Washington, NY 11050 Phone (516) 515.5000 • Fax (516) 515.5050 **Western Distribution Center** 1750 Archibald Avenue • Ontario, CA 91760 Phone (800) 526.2588 • Fax (800) 526.2585

WAC Lighting retains the right to modify the design of our products at any time as part of the company's continuous improvement program. JUN 2013

- Minimizes wiring back to transformer
- No voltage drop, power supplied using a variable current
- If one fixture goes out the rest remain on