



FIGURE 1.2

A → B → C → D → E → F → G → H

1. Carefully unpack and identify the parts. (Refer to the illustration above (Figure 1.2)).
2. Thread The Stem (Part B) into the Coupling located at the bottom center of the Fixture Body (Part A).
3. Insert the Glass (Part C), Rubber Washer (Part D) and Steel Washer (Part E) into the Stem (Part B) and tightly secure the connection by threading it with the Hex Nut (Part F).
4. Install the Cup (Part G) into the Stem (Part B) and tightly secure the connection by threading it with the finial (Part H).

Note: Please refer to the "Mounting and Wiring instruction Sheet" for the wiring connections.
Please refer to the Markings and labels on the fixture for the maximum wattage limit.
(Bulb not included)

MOUNTING AND WIRING INSTRUCTIONS

1. Turn machine screws (provided) into mounting strap using the threaded holes in the mounting strap that align with the holes in the canopy.

2. Fasten mounting strap to junction box with machine screws found in junction box. The mounting strap must be used to provide proper grounding of fixture.

3. Pull leads down out of junction box for easier wiring. Connect the IDENTIFIED lead (white, tinned or ribbed - if both conductors are the same color, feel for the ribbed edge that runs the entire length of one side) to the WHITE house wire. Connect the UNIDENTIFIED lead to the BLACK house wire. Turn the green ground screw into the hole in the mounting strap and wrap the bare ground wire around screw one full turn and tighten screw. Connect remaining end of bare wire to the house ground wire (bare). If the junction box itself is metal and is already grounded, attachment to the green screw only is sufficient. Always use wire connectors that are UL approved for the size and number of wires to be connected.

Caution: Never connect the bare ground wire to the black or white house wires.

4. Place all wires and connectors back into junction box making sure there are no loose wire nuts or bare leads. Place canopy up against ceiling allowing the machine screws to protrude through the two canopy holes. Be careful not to pinch any wires between the canopy and the ceiling.

5. Turn ballnuts onto machine screws until canopy is firmly against ceiling.

6. Lamp fixture with proper size bulbs in accordance with the wattage label found on the fixture.

