

### MonoRail Remote Kit 300w



**DESCRIPTION**

Includes 8' long hand-bendable MonoRail, two sets of decorative end caps, two rigid standoffs, a power feed canopy and a 12 volt 300 watt remote magnetic transformer. Rail drops 2" from ceiling. Add up to six 50 watt elements or up to eight 35 or 37 watt elements.

**INSTALLATION**

Magnetic transformer installs in an accessible location behind the ceiling or wall. Canopy mounts to a standard 4" junction box with round plaster ring (provided by electrician) and includes 24" softwire leads.

**DIMMING**

Dimmable with a 600 watt low-voltage magnetic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics.)

**ORDERING INFORMATION**

**700MOKTA300** FINISH

- Z ANTIQUE BRONZE
- C CHROME
- S SATIN NICKEL



**TECH LIGHTING®**

7400 Linder Avenue                      T 847.410.4400  
Skokie, Illinois 60077                      F 847.410.4500

[www.techlighting.com](http://www.techlighting.com)

700MOKTA300 \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_

\_\_\_\_\_  
\_\_\_\_\_



©2010 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.