

Ρ	Product Specifications for E94911-54SN					
	Job Name:	Job Type:				
		21				
	Quantity:	Comments				



**ADA** 

## E94911-54SN

Minx 4-Light RapidJack Pendant and Canopy

34.5"

Finish	Glass/Shade	Product Category
Satin Nickel	Translucent Frost	

Lamping		Measurements		Shipping
Number of Bulb(s)	4	Width	4.25"	Carton We
Light Type	Xenon	Height	8.50"	Carton Wi
Bulb Type	12V GY6.35 T4	Length	34.25"	Carton He
Max Bulb Wattage	50	Extension	N/A	Carton Le
Max Fixture Wattage	200	Back Plate Width	N/A	Carton Cu
Rated Life	±2,000 Hours	Back Plate Height	N/A	<b>Master Pa</b>
Rated Lumens	±3,000	HCO	N/A	Master Pa
Color Temp	±2,900 K	Min Overall Height	N/A	Master Pa
Bulb(s) Included	Yes	Max Overall Height	130.75"	Master Pa
Light Up/Down	N/A	Hanging Weight	N/A	Master Pa
Beam Spread	N/A	Height Adjustable	Yes	Master Cu
CRI	N/A	Slope	N/A	UPS Ship
Photo Cell Included	N/A	Chain Length	N/A	
Ballast/Driver/Transformer	Yes	Wire Length	63.00"	
Dimmable	Low-Voltage	Canopy Width	4.5"	
		Canopy Height	2.3"	

Jilippilig	
Carton Weight	N/A
Carton Width	7.08"
Carton Height	12.00"
Carton Length	7.08"
Carton Cubic Feet	N/A
Master Pack	1
Master Pack Weight	N/A
Master Pack Width	N/A
Master Pack Height	N/A
Master Pack Length	N/A
Master Cubic Feet	N/A
UPS Shippable	Yes

## Certification Other Equivalents

No

**Canopy Length** 

			4	
Safety Rating	Dry UPC Cod	<b>e</b> 845094044505	Incandescent Watts	N/A
Energy Star	No <b>Material</b>	N/A	Fluorescent Watts	N/A
CA Title 24	No			
CA Title 20	No			

ET2 Contemporary Lighting and all designs, logos and images © 2014 ET2 Contemporary Lighting. All Rights Reserved. ET2 Contemporary Lighting reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes. Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.