

Product Specifications for E94906-10SN			
	Job Name:	Job Type:	
	Quantity:	Comments	



**ADA** 

## E94906-10SN

Minx 4-Light RapidJack Pendant and Canopy

34.5"

Finish	Glass/Shade	Product Category
Satin Nickel	Opal White	

Lamping		Measurements		Shipping
Number of Bulb(s)	4	Width	3.75"	Carton Weight
Light Type	Xenon	Height	2.75"	Carton Width
Bulb Type	12V G4	Length	34.25"	Carton Height
Max Bulb Wattage	20	Extension	N/A	Carton Length
Max Fixture Wattage	80	Back Plate Width	N/A	Carton Cubic F
Rated Life	±2,000 Hours	Back Plate Height	N/A	Master Pack
Rated Lumens	±1,280	HCO	N/A	Master Pack W
Color Temp	±2,900 K	Min Overall Height	N/A	Master Pack W
Bulb(s) Included	Yes	Max Overall Height	125.00"	Master Pack He
Light Up/Down	N/A	Hanging Weight	N/A	Master Pack Le
Beam Spread	N/A	Height Adjustable	Yes	Master Cubic F
CRI	N/A	Slope	N/A	<b>UPS Shippable</b>
Photo Cell Included	N/A	Chain Length	N/A	
Ballast/Driver/Transformer	Yes	Wire Length	63.00"	
Dimmable	Low-Voltage	Canopy Width	4.5"	
		Canopy Height	2.3"	

.75"	Carton Weight	N/A
.75"	Carton Width	7.00"
.25"	Carton Height	8.00"
N/A	Carton Length	7.00"
N/A	Carton Cubic Feet	N/A
N/A	Master Pack	1
N/A	Master Pack Weight	N/A
N/A	Master Pack Width	N/A
.00"	Master Pack Height	N/A
N/A	Master Pack Length	N/A
Yes	Master Cubic Feet	N/A
N/A	UPS Shippable	Yes
N/A		
00"		

N/A N/A

## Certification Other Equivalents

No

**Canopy Length** 

Safety Rating	Dry	UPC Code	845094044468	Incandescent Watts
Energy Star	No	Material	N/A	Fluorescent Watts
CA Title 24	No			
CA Title 20	No			

ET2 Contemporary Lighting and all designs, logos and images © 2014 ET2 Contemporary Lighting. All Rights Reserved. ET2 Contemporary Lighting reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes. Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.