WARNING

WE RECOMMEND INSTALLATION OF THIS LIGHTING FIXTURE BE DONE BY A LICENSED ELECTRICIAN.

WARNING *** SWITCH OFF THE MAIN ELECTRICAL SUPPLY FROM THE MAIN FUSE BOX/CIRCUIT BREAKER BEFORE INSTALLATION.

INSPECT ITEM CAREFULLY BEFORE ATTEMPTING TO INSTALL. IF THERE IS ANY DAMAGE OR OBVIOUS DEFECT, DO NOT INSTALL. ITEM MAY NOT BE RETURNED ONCE IT HAS BEEN INSTALLED.

CARE AND MAINTENANCE

To clean the outside of the fixture, use a dry or slightly dampened clean cloth (use clean water, never a solvent) to wipe the surface of the fixture.

To clean the inside of the fixture, first disconnect power to the fixture by turning off the circuit breaker or by removing the fuse at the fuse box. Next, use a dry or slightly dampened clean cloth (use clean water, never a solvent) to wipe the interior surface of the fixture.

Do not use any cleaners with chemical, solvents or harsh abrasives. Use only a dry soft cloth to dust or wipe carefully.

NOTICE& IMPORTANT SAFETY INSTRUCTIONS

- * Please make sure that you have all parts indicated before you begin assembly of this item
- * This item should be assembled on a soft surface to prevent scratching the finish during assembly
- * To reduce the risk of fire, electrical shock or injury to persons or property, please follow the guideline below for safe use

and installation


*The external flexible cable or cord of this lamp cannot be replaced If the cord is damaged, the lamp shall be destroyed

Part List and Hardware List

r dit Elot dila ridi awaro Elot								
PIECE	DESCRIPTION	PICTURE	QUANTITY	PIECE	DESCRIPTION	PICTURE	QUANTITY	
Α	machine screw	(S)	2X	F	glass shade		5X	
В	mounting screw	(Quantum	2X	G	Nut cap		2X	
С	mounting bracket	Ô	1X	Н	ShadeScrew	F	15X	
D	ground screw		1X	I	bulb	\Diamond	5X	
Е	wire connector	0	3X		Lampbody		1X	



Model#: JYL9555
Product Dimensions:
38"L X 7.25"WX12. 25"H



PREPARATION

Before beginning assembly of product, make sure all parts are present. Compare parts with package contents list and hardware contents list. If any part is missing or damaged, do not attempt to assemble the product.

Estimated Assembly Time: 20 minutes.

If there are any questions relating to defects, missing parts, assembly issues, replacements, or device connectivity issues, please send a detailed email to cs@jonathany.com

- 1.Separate the Mounting Plate(B) from the Lampbody(J) by removing the Canopy Screw(G) anti-clockwise.
- 2.Attach the Mounting Plate(B) onto the J-box and secure it by turning 2 Mounting Screws(C)clockwise till tight.

Connect, Hot, Black or Red Outlet Supply Wire to:	Connect, Neutral, White Outlet Supply Wire to:		
Black	White		
* Parallel Cord (round & smooth)	* Parallel Cord (square & ridged)		
Clear, Brown, Gold or Black without Tracer	Clear, Brown, Gold or Black with Tracer (colored		
(colored stripes)	stripes)		
Insulated Wire (not green) with copper metal	Insulated Wire (not green) with Silver metal		
conductor	conductor.		



*Note: When parallel wire (SPT I & SPT II) is used. The neutral wire is square shaped

Grounding Instructions:

- a) For installation in the United States: Wrap ground wire from outlet box around green ground screw(D) on mounting bracket, no less than 2" from wire end. Tighten ground screw. If fixture is supplied with a ground wire, connect to outlet ground wire with a wire connector.
- b) For installation in Canada: If fixture is supplied with ground wire, wrap ground wire around green grounding screw on mounting bracket. Tighten ground screw.
- 3. Unscrew the Shade Screws(H) from the Lampbody(J).
- 4. Insert the bulbs (I) into the Sockets. Be sure to use light bulb(I) with wattage no greater than specified on this fixture. Make sure that electrical current is turned off before changing bulbs.
- 5. Place the Glass Shades(F) over the sockets and fix them in place by turning the Shade Screws(H) clockwise till tight.

PLEASE USE TYPE"B" BULB MAX 25-WATT OR CFL BULB MAX 9-WATT OR LED BULB 5W THERE ARE 5 X 4W LED BULBS IN THE BOX.

ENJOY YOUR LAMP

