



Catalog Number
Notes
Type

Contractor Select™

WPD

Phase Dimming Wall Switch

The Sensor Switch WPD is an economical commercial grade forward phase paddle dimmer for LED, CFT, Incandescent, and self ballast devices. The WPD allows the user or installer to set high and low trim settings and return to default easily and efficiently. Its elegant design does not compromise function, whereas this device offers extremely smooth dimming control that meets NEMA SSL-7A requirements.

FEATURES:

- Perfect Replacement for regular wall ON/OFF & Dim switch, 120VAC
- Manual ON/OFF& Dim control of any permanently installed incandescent, dimmable LED, and CFL lamp fixture
- Preset light level option allows the dimmer will turn on to the light level that it was adjusted to the previous time when the light was on
- Can be used for single pole or 3-way control with a regular ON/OFF mechanical switch (sold separately)
- Capable of setting maximum and minimum dimming range (see installation instructions)
- Air-Gap Switch feature meets UL requirements and disconnects power from load locally
- Programming Status LED Indicator
- Includes screw-less wall plate
- Fully Meet NEMA SSL -7A



Catalog Number	UPC	Description	Voltage Type	Color	Voltage	Pallet Quantity
WPD WH	194994217374	Phase Dimming Wall Switch	Line	White	120V	100



Specifications

INSTALLATION:

- **WARNING:** To avoid fire, shock, or death. High Voltage - Turn off power at circuit breaker or fuse and test that power is off before wiring.
- **CAUTION:** To reduce the risk of overheating and possible damage to other equipment, **DO NOT** install to control a receptacle, a motor-operated appliance, a fluorescent lighting fixture, or a transformer supplied appliance.
- Remove wall plate and existing switch mounting screws.
- Carefully remove the existing switch from the switch box.
- Disconnect the wiring from the existing switch.
- Connect the dimmer switch as shown in the wiring diagram: Black lead to hot wire, white lead to neutral wire, red lead to load wire, green lead to ground wire.
- Check connections to be sure they are tight, and no bare conductors are exposed.
- Insert the WPD dimmer switch into the standard outlet box carefully.
- Make sure the WPD dimmer switch supplied screws in designated location.
- Attach the wall plate.
- Restore power at the circuit breaker and test the system.

LISTINGS:

cULus Listed

For use in ambient operating temperatures ranging from - 0°C to 40°C.

WARRANTY:

5-year limited warranty. Complete warranty terms located at:

www.acuitybrands.com/support/warranty/terms-and-conditions

Note: Actual performance may differ as a result of end-user environment and application. Specifications subject to change without notice.

Dimensions

2.61"H x 1.90"W x 1.56"D (66.5mm x 48.2mm x 39.5mm)