

Kable Lite Surface Transformer-600W Mag**DESCRIPTION**

This dual-feed surface transformer converts standard 120 volt line-voltage to 12 volts to provide the necessary voltage for powering a Kable Lite system. It can power lamps totaling up to 600 watts. The transformer is concealed inside a decorative housing equipped with two fast-acting secondary circuit breakers that will safely turn off the system should a short occur. Once the short has been removed the breaker can be reset.

INSTALLATION


This product can mount to either a standard 4" square electrical box with round plaster ring or an octagon electrical box (not included). Isolating connectors (included) isolate the two power feeds from each other.

DIMMING

Dimmable with a 1000 watt low-voltage magnetic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics). This surface transformer includes a preinstalled debuzzing dimming coil to reduce audible noise when using a low-voltage dimmer.

OTHER INFORMATION

Black and white finish have chrome feeds. The shortest rigid standoff that can be used with this surface transformer is the 5" rigid post standoff (sold separately). This surface transformer may be plugged in with the addition of a Plug Option, a 16' cord with plug (sold separately). 12 volt transformers require the use of 12 volt lamps.

**WEIGHT**

20.4lb / 9.25kg

ORDERING INFORMATION**700SRT60D FINISH**

- Z** ANTIQUE BRONZE
- B** BLACK
- C** CHROME
- S** SATIN NICKEL
- W** WHITE



TECH LIGHTING®

7400 Linder Avenue
Skokie, Illinois 60077

T 847.410.4400
F 847.410.4500

www.techlighting.com

700SRT60D _____

Fixture Type: _____

Job Name: _____

Notes: _____



©2011 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.