

INSTRUCTIONS

Class 2 Power Unit Model EN-2460D-C

CAUTION – TO REDUCE RISK OF FIRE AND ELECTRICAL SHOCK

- Always turn off power at main switch prior to installation.
- Intended for installation by a qualified electrician.
- System is intended for installation in accordance with National Electric Code, and local regulations. Consult with local inspector to assure compliance.

MAX LOAD	60W
INPUT VOLTAGE	120-240V 60Hz
INPUT CURRENT	1.2A
OUTPUT CURRENT	2.5A
OUTPUT VOLTAGE	24V DC
CASE TEMP	40 °C to 55 °C
AMBIENT TEMP	-4 to 122 °F (-30°C to 70°C)
MINIMUM LOAD	1.5W

FEATURES:

- Power Supply short circuit protection with auto-reset.
- Overload protection with auto-reset.
- Automatic thermal regulation.
- Soft start delay to preserve bulb life, for use with controller

INSTALLATION

- DC power supply must be installed away from heat sources and accessible for service
- Enclosed DC power supply is UL listed. The power supply box has a separate line volt, and low volt wiring compartments. Trade size knock out are provided on both compartments. Connect building wires to like color DC power supply wires with wire nuts. Building ground wire may be green or un-insulated, and attaches to green wire from DC power supply box.

