MOVENTO

MOVENTO 769. Heavy Duty

Ablum

Application




Features

- Four-dimensional adjustment
- Elongated holes for depth adjustment
- 170 lb static load capacity

Description

- Full extension concealed runners
- Frameless or blocked-out face frame cabinets
- BLUMOTION soft closing
- Smooth running action
- Available in 18" to 30" lengths
- 13 (1/2") to 16 (5/8") drawer thickness
- Compatible with TIP-ON BLUMOTION and SERVO-DRIVE

Basic Components



Components

Runner set

One set required per drawer



For overall cabinet depth	Drawer length	MOVENTO	
838 (33")	762 (30")	769.7620S	
762 (30")	686 (27")	769.6860S	
686 (27")	610 (24")	769.6100S	
610 (24")	533 (21")	769.5330S	
533 (21")	457 (18")	769.4570S	
Wood screw for installation	606N or 606P		
System screw for installa	662.1150.HG		

NOTE: For 769. series runners, rear brackets and sockets cannot be used. Cabinet sides must be blocked-out flush with the inside of the frame. See page 13.

Standard locking device with side-to-side adjustment

- One right and one left required per drawer
- Captive right and self-aligning left device
- Self-adjusting drawer length tolerance
- Steel base with synthetic, spring-loaded release levers
- Minimum inside drawer width 170 (6-11/16")
- Side-to-side adjustment ±1.5 (1/16")
- For use with MOVENTO runners only -
- For other options see page 26

Part no.

	Right locking device	T51.7601 R
Installation	Left locking device	T51.7601 L
page 7	Installation screw	606N or 606P

Locking device spacer for thin fronts

 Works with MOVENTO locking devices 12 (15/32") and 13 (1/2") sub-fronts only

Part no.

```
T59.K010M
6064N
```

- Enables MOVENTO drawers to be opened with just a light touch of the drawer front and retain BLUMOTION soft closing action
- Fully mechanical motion

Optional TIP-ON BLUMOTION


- Can be used with or without pulls
- Minimum opening width 281 (11-1/16")

Drawer and Cabinet Specifications

Maximum drawer thickness 16 (5/8") Lengths available 18" - 30" Static load capacity 170 lb


MOVENTO






NOTE: Drawer side material thickness may vary. Accurate measurement of drawer side material thickness should be used when calculating outside drawer width using the table below. Inside drawer width **must** equal opening width minus **42** (1-21/32") for MOVENTO runners to align and function optimally.


Calculating outside drawer width						
For drawer side thickness	16 (5/8")	15 (19/32")	13 (1/2")	12 (15/32")		
Deduct from opening width	10 (13/32")	12 (15/32")	16 (5/8")	18 (23/32")		
Example: For 21" opening width and a 5/8" thick drawer, 21" minus 13/32" = 20-19/32" drawer width						





Runner mounting specifications





NOTE: Elongated holes are for \pm **4.5** (3/16") depth adjustment only. Additional screws must be used to secure the runner to the cabinet.

NOTE: The orange dots indicate fixing screw locations required to meet specified load ratings

NOTE: If using 15/32" or 1/2" drawer thickness without T59.K010M, subtract 3 (1/8") from setback and screw locations.

MOVENTO Drawer length	Drawer	Minimum inside	Runner	Screw location	
	cabinet depth	length	А	В	
769.7620S	762 (30")	782 (30-13/16")	773 (30-7/16")	261 (10-9/32")	389 (15-5/16")
769.6860S	686 (27")	706 (27-13/16")	697 (27-7/16")	261 (10-9/32")	389 (15-5/16")
769.6100S	610 (24")	630 (24-13/16")	621 (24-7/16")	261 (10-9/32")	389 (15-5/16")
769.5330S	533 (21")	553 (21-13/16")	544 (21-7/16")	261 (10-9/32")	357 (14-1/16")
769.4570S	457 (18")	477 (18-13/16")	468 (18-7/16")	261 (10-9/32")	357 (14-1/16")

NOTE: 24", 27", and 30" length MOVENTO runners must be raised 3 (1/8") for inset face frame applications