BRUCK.

Job Name:

Contact:

Fixture Type:

Part Number:

Description:

The 150W electronic Enzis transformer can be mounted over a standard 4" junction box to supply a maximum of 150W. The Enzis 150W Direct Feed Transformer is for use with the Enzis system only, and is available in plated bronze, matte chrome or polished chrome finish.

ENZIS 150W DIRECT FEED TRANSFORMER

Part Numbers:240340bzbronze240340mcmatte c

matte chrome

Technical Specs:

150VA maximum (20VA minimum) 120V AC, 50/60Hz input 11.7V AC output Suitable for dry locations only Mount to 3" - 4" round J-box Short circuit protection Overload protection Thermal protection Dimmable

