


Job Name: Contact:

Fixture Type: Part Number:

TQ-150 REMOTE TRANSFORMER



Description:

The TQ-150 series magnetic remote transformer features a metal enclosure with a covered wiring compartment, which can be surface or recessed mounted in a wall and is equiped with debuzzing choke for dimming applications. The additional tap outputs can be used to counter voltage drop do to longer power feeds. A toroidal coil is used for reliability and efficient operation. Please contact manufacturer for further details.

Part Numbers:


TQ-150/120v white, 150VA, 120v

Technical Specs:

120V AC, 60Hz input 11/12/13/14/15V AC output

Auto thermo shutoff (resettable) and switch circuit breaker on primary

15A switch circuit breaker on secondary 25 x 1/2" electrical connect knockouts



 Bruck Lighting System, Inc.
 15774 Gateway Circle
 Tustin, CA 92780
 p:714.259.9959
 f:714.259.9969
 24 May 2010