

## MACH 120°

Master Switch module

switch.

35/8

(NMS-1) controls a run of Mach 120 with a single

SPEED&LINK

11/8

Project \_\_\_\_\_ Fixture Type \_\_\_\_\_



Dimensions	Lamps	White - WT	Bronze - BZ	Satin Aluminum - SA
<b>16"</b> 16"L x 3⁵‰"W x 11⁄‰"H	2	NMA120L-16WT	NMA120L-16BZ	NMA120L-16SA
35W 120V Xenon Lamp	S	Lamp	120V: L-35	
no transformers 35W		35W Xenon Type JCD, G-8 Base Clear, 270 lumen WT-White, BZ- Bronze, SA-Satin Aluminum		

## MACH 120® FEATURES

- Three power options Hardwire through knockouts, Interconnected with SpeedLink<sup>™</sup> technology or Portable with cord and plug option
- 35W/120V Long-life Xenon lamps included
- Optional Master Switch allows single switch control of a run of Mach 120 when a wall switch is not available
- 120V Long-life xenon lamps 20 Lamps with one power feed when linking.
- Fast easy installation furnished complete with mounting hardware
- · Internal connectors allow instant hardwiring without wire nuts
- Knockouts on back for Romex, flex or rigid conduit ½" MC connector included with each fixture
- Extruded aluminum construction
- · Porcelain Sockets used for high temperature tolerance
- · Glass prismatic diffuser for maximum light distribution
- Hinged glass door no tools required for relamping
- · Hi-Off-Lo switch, dimmable, energy saving
- Multiple US patents pending

US C

