

Electronic Low Voltage Cylinder Track Fixture



Features

- Use with 1 or 2 circuit track and accessories.
- Includes Transformer.
- Lamp: 12V MR16 (50W or 75W)

Specifications

Wattage	50W - 75W
Voltage	12V
Damp Location	Listed

Technical Details

Construction: Meticulously manufactured track fixture with a clean powder coated finish for lasting quality.

Adjustability: Track head is adjustable 180° vertically with 358° rotation.

Lamp: Compatible with BiPin GU5.3 MR16 lamps. (Lamp not included).

Installation: Effortlessly installed into H-Style track from ELCO or others. Compatible with Single and Double circuit track. Can be ordered as J-Style or L-Style.

Electrical: Solid state electronic Low Voltage Transformer is compatible with 20W to 50W lamps or 20W to 75W lamps. Designed for noiseless operation.

Dimmability: Works with 120V electronic low voltage rated dimmers. Dims down to 10%. For full list of dimmers, refer to the Dimmer Compatibility List.


Listings:

- ETL Listed
- RoHS Compliant

Options



Copper



All White



All Black



All Bronze




Gold



All Nickel

Dimensions



Product Numbers

Item	Watts	Voltage	Finish
ET528B	50W	12V	All Black
ET528-75B	75W	12V	All Black
ET528BZ	50W	12V	All Bronze
ET528CP	50W	12V	Copper
ET528G	50W	12V	Gold
ET528N	50W	12V	All Nickel
ET528W	50W	12V	All White
ET528-75W	75W	12V	All White