


assembly instructions




Family: Plantation | Item No. 2226 CB / 2126 PZ

Ystart here








- 1. Find a clear area in which you can work.
- 2. Unpack fixture and glass from carton.
- 3. Carefully review instructions prior to assembly.


Drawing 2 - Fixture Mounting



*** The construction of this fixture will be accomplished by first mounting the mounting strap to the junction box, making all necessary electrical connections, mounting the fixture to the wall, and then installing the glass.

- 1. Prepare mounting strap (A) by threading the two 1 1/4" long mounting screws (B) into the back of the gull wing bracket - see Drawing 1.
 - Be sure the holes into which the screws are threaded match the spacing of holes (D) in the back plate (E) - see Drawings 1 and 2.
 - 2. Attach mounting strap (A) to junction box (J) using two 1" screws (C) provided see Drawing 2.

Drawing 3 - Glass Installation



SAFETY WARNING: READ WIRING AND GROUNDING INSTRUCTIONS (I.S. 18) AND ANY ADDITIONAL DIRECTIONS. TURN POWER SUPPLY OFF DURING INSTALLATION. IF NEW WIRING IS REQUIRED, CONSULT A QUALIFIED **ELECTRICIAN OR LOCAL AUTHORITIES FOR CODE REQUIREMENTS.**

Make electrical connections from supply wire to fixture lead wires. Refer to instruction sheet (I.S. 18) and follow all instructions to make all necessary wiring connections. Then refer back to this sheet for glass installation instructions.

- 1. Slide backplate (E) over screws (B) and secure with ball knobs (F) see Drawing 2.
- 1. Prior to installing glass, fixture can now be lamped accordingly.
- 2. To install glass, slip glass (2) over the bulb and onto fixture and hold in place see Drawing 3.
- 3. Thread the three thumb screws (1) provided and tighten against glass (2).

Note: Maximum wattage for 2226 / 2126 fixture is 60 watts per bulb.

2.7.08