



design • illuminate • enjoy


assembly instructions

Family: Edgewater | Item No. 1683 MR/VK






Drawing 2 - Fixture Mounting



2

5

Drawing 3 - Glass Installation



Start here

- 1. Find a clear area in which you can work.
 - 2. Unpack fixture and glass from carton.
 - 3. Carefully review instructions prior to assembly.

*** The construction of this fixture will be accomplished by first mounting the mounting strap to the junction box, making all necessary electrical connections, hanging the fixture from the ceiling, and then installing the glass.

- 1. Prepare gem strap (A) for mounting by threading two screws (B) provided into back of gull wing bracket of gem strap (A) - see Drawing 1.
- Be sure the holes into which the screws are threaded match the spacing of holes (D) in the ceiling pan (1) - see Drawings 1 and 2.
- 3. Mount gem strap (A) to junction box (J), using the two 1" screws (C) provided.

SAFETY WARNING: READ WIRING AND GROUNDING INSTRUCTIONS (I.S. 18) AND ANY ADDITIONAL DIRECTIONS. TURN POWER SUPPLY OFF DURING INSTALLATION. IF NEW WIRING IS REQUIRED, CONSULT A QUALIFIED ELECTRICIAN OR LOCAL AUTHORITIES FOR CODE REQUIREMENTS.

- Make electrical connections from supply wire to fixture lead wires. Refer to instruction sheet (I.S. 18) and follow all instructions to make all necessary wiring connections. Then refer back to this sheet to continue installation of this fixture.
 - 1. Hang the fixture by slipping the holes (D) in the ceiling pan (1) over the screws (B) in the mounting strap (A) - see Drawing 2.
 - 2. Thread on ball knobs (F) to secure fixture to the ceiling.
 - 1. Before installing glass, fixture can now be lamped accordingly.
 - 2. To install bottom panel of glass (2), thread nipple (3) into coupler (4).
 - 3. Slip glass panel (2) over nipple (3) and hold in place.
 - 4. Thread knob (5) onto nipple (3) and hand tighten only. Note: tightening with a tool may cause damage to glass.

Note: Maximum wattage for 1683 fixture is 60 watts per bulb.