

Operating Instructions and Parts Manual Horizontal/Vertical Bandsaw Model: HVBS-56M





WALTER MEIER (Manufacturing) Inc.

427 New Sanford Road LaVergne, Tennessee 37086 Ph.: 800-274-6848 www.waltermeier.com

Warranty and Service


Walter Meier (Manufacturing) Inc., warrants every product it sells. If one of our tools needs service or repair, one of our Authorized Service Centers located throughout the United States can give you quick service. In most cases, any of these Walter Meier Authorized Service Centers can authorize warranty repair, assist you in obtaining parts, or perform routine maintenance and major repair on your JET_® tools. For the name of an Authorized Service Center in your area call 1-800-274-6848.

MORE INFORMATION

Walter Meier is consistently adding new products to the line. For complete, up-to-date product information, check with your local Walter Meier distributor, or visit waltermeier.com.

WARRANTY

JET products carry a limited warranty which varies in duration based upon the product (MW = Metalworking, WW = Woodworking).



WHAT IS COVERED?

This warranty covers any defects in workmanship or materials subject to the exceptions stated below. Cutting tools, abrasives and other consumables are excluded from warranty coverage.

WHO IS COVERED?

This warranty covers only the initial purchaser of the product.

WHAT IS THE PERIOD OF COVERAGE?

The general JET warranty lasts for the time period specified in the product literature of each product.

WHAT IS NOT COVERED?

Five Year Warranties do not cover woodworking (WW) products used for commercial, industrial or educational purposes. Woodworking products with Five Year Warranties that are used for commercial, industrial or education purposes revert to a One Year Warranty. This warranty does not cover defects due directly or indirectly to misuse, abuse, negligence or accidents, normal wear-and-tear, improper repair or alterations, or lack of maintenance.

HOW TO GET SERVICE

The product or part must be returned for examination, postage prepaid, to a location designated by us. For the name of the location nearest you, please call 1-800-274-6848.

You must provide proof of initial purchase date and an explanation of the complaint must accompany the merchandise. If our inspection discloses a defect, we will repair or replace the product, or refund the purchase price, at our option. We will return the repaired product or replacement at our expense unless it is determined by us that there is no defect, or that the defect resulted from causes not within the scope of our warranty in which case we will, at your direction, dispose of or return the product. In the event you choose to have the product returned, you will be responsible for the shipping and handling costs of the return.

HOW STATE LAW APPLIES

This warranty gives you specific legal rights; you may also have other rights which vary from state to state.

LIMITATIONS ON THIS WARRANTY

WALTER MEIER (MANUFACTURING) INC., LIMITS ALL IMPLIED WARRANTIES TO THE PERIOD OF THE LIMITED WARRANTY FOR EACH PRODUCT. EXCEPT AS STATED HEREIN, ANY IMPLIED WARRANTIES OR MERCHANTABILITY AND FITNESS ARE EXCLUDED. SOME STATES DO NOT ALLOW LIMITATIONS ON HOW LONG THE IMPLIED WARRANTY LASTS, SO THE ABOVE LIMITATION MAY NOT APPLY TO YOU.

WALTER MEIER SHALL IN NO EVENT BE LIABLE FOR DEATH, INJURIES TO PERSONS OR PROPERTY, OR FOR INCIDENTAL, CONTINGENT, SPECIAL, OR CONSEQUENTIAL DAMAGES ARISING FROM THE USE OF OUR PRODUCTS. SOME STATES DO NOT ALLOW THE EXCLUSION OR LIMITATION OF INCIDENTAL OR CONSEQUENTIAL DAMAGES, SO THE ABOVE LIMITATION OR EXCLUSION MAY NOT APPLY TO YOU.

Walter Meier sells through distributors only. The specifications in Walter Meier catalogs are given as general information and are not binding. Members of Walter Meier reserve the right to effect at any time, without prior notice, those alterations to parts, fittings, and accessory equipment which they may deem necessary for any reason whatsoever. JET⊚branded products are not sold in Canada by Walter Meier.

Table of Contents

Warranty and Service	2
Table of Contents	3
Warning	4
Minimum gage for cord	
Grounding Instructions	6
Specifications	
Unpacking and Clean-Up	
Tools Supplied for Assembly	
Tools Required for Assembly	8
Assembly	8
Vertical Cutting Plate Assembly	10
Electrical Connections	11
Changing Blade Speed	12
Adjusting Blade Guides	12
Adjusting Blade Tension	12
Changing Blades	
Adjusting Blade Guide Bearings	13
Adjusting Blade Tracking	14
Adjusting Feed Pressure	14
Blade-Table Squareness	15
Adjusting Automatic Shut-Off	15
Adjusting the Vise	15
Lubrication	16
Breakdown for Bow Assembly	17
Breakdown for Base Assembly	18
Parts List for the HVBS-56M Bandsaw	19
Wiring Diagram	22



Read and understand the entire instruction manual before operating machine.

This bandsaw is designed and intended for use by properly trained and experienced personnel only. If you are not familiar with the proper and safe use of a bandsaw, do not use until proper training and knowledge have been obtained.

"Warning: For you own safety read instruction manual before operating saw."

- a) Wear eye protection.
- b) Do not remove jammed cut off pieces until blade has stopped.
- c) Maintain proper adjustment of blade tension, blade guides, and thrust bearing.
- d) Adjust upper guide to just clear workpiece.
- e) Hold workpiece firmly against table.
- 1. Keep guards in place and in working order.
- 2. Remove adjusting keys and wrenches. Form a habit of checking to see that keys and adjusting wrenches are removed from the machine before turning it on.
- 3. Keep work area clean. Cluttered areas and benches invite accidents.
- 4. Don't use in dangerous environment. Don't use power tools in damp or wet locations, or expose them to rain. Keep work area well lighted.
- 5. Keep children away. All visitors should be kept a safe distance from the work area.
- 6. Make your workshop child proof with padlocks, master switches or by removing starter keys.
- 7. Don't force tool. It will do the job better and more safely at the rate for which it was designed.
- 8. Use the right tool at the correct speed and feed rate. Do not force a tool or attachment to do a job for which it was not designed.
- 9. Use proper extension cord. Make sure your extension cord is in good condition. When using an extension cord, be sure to use one heavy enough to carry the current your product will draw. An undersized cord will cause a drop in voltage resulting in loss of power and overheating. Table 1 shows the correct size to use depending on cord length and nameplate ampere rating. If in double, use the next heavier gage. The smaller the gage number, the heavier the cord.
- 10. Wear proper apparel. Do not wear loose clothing, gloves, neckties, rings, bracelets, or other jewelry which may get caught in moving parts. Nonslip footwear is recommended. Wear protective hair covering to contain long hair.
- 11. Always wear approved safety glasses/face shields while using this bandsaw. Also use face or dust mask if cutting operation is dusty. Everyday eyeglasses only have impact resistant lenses; they are NOT safety glasses.
- 12. Secure work. Use clamp or vise to hold work when practical. It is safer than using your hand and it frees both hands to operate tool.
- 13. Don't overreach. Keep proper footing and balance at all times.
- 14. Maintain tools with care. Keep tools sharp and clean for the best and safest performance. Follow instructions for lubricating and changing accessories.
- 15. Disconnect tools before servicing; when changing accessories such as blades, bits, cutters, and the like.
- 16. Reduce the risk of unintentional starting. Make sure switch is in off position before plugging in.
- 17. Use recommended accessories. Consult the owner's manual for recommended accessories. The use of improper accessories may cause risk of injury to persons.
- 18. Never stand on tool. Serious injury could occur if the tool is tipped or if the cutting tool is unintentionally contacted.

- 19. Some dust created by power sanding, sawing, grinding, drilling and other construction activities contain chemicals known to cause cancer, birth defects or other reproductive harm. Some examples of these chemicals are:
 - Lead from lead based paint.
 - Crystalline silica from bricks, cement and other masonry products.
 - Arsenic and chromium from chemically treated lumber.

Your risk of exposure varies, depending on how often you do this type of work. To reduce your exposure to these chemicals, work in a well-ventilated area and work with approved safety equipment, such as face or dust masks that are specifically designed to filter out microscopic particles.

- 20. Check damaged parts. Before further use of the machine, a guard or other part that is damaged should be carefully checked to determine that it will operate properly and perform its intended function. Check for alignment of moving parts, binding of moving parts, breakage of parts, mounting and any other conditions that may affect its operation. A guard or other part that is damaged should be properly repaired or replaced.
- 21. Feed work into a blade or cutter only against the direction of rotation of the blade or cutter.
- 22. Never leave tool running unattended. Turn power off. Don't leave tool until it comes to a complete stop.
- 23. Give your work undivided attention. Looking around, carrying on a conversation and "horse-play" are careless acts that can result in serious injury.
- 24. Do not operate this machine while tired or under the influence of drugs, alcohol or any medication.
- 25. Never leave the machine running unattended. Turn the power off and do not leave the machine until it comes to a complete stop.
- 26. Turn off the machine before cleaning. Use a brush or compressed air to remove chips or debris do not use your hands.

Minimum gage for cord

		Volts	Total length of cord in feet			
		120V	25 ft.	50ft.	100ft.	150ft.
Ampere Rating		240V	50ft.	100ft.	200ft.	300ft.
	Not					
More	More					
Than	Than			AWG		
0	6		18	16	16	14
6	10		18	16	14	12
10	12		16	16	14	12
12	16		14	12	Not Recommended	

Only the applicable parts o the Table need to be included, For instance, a 120-volt product need not include the 240-volt heading

Table 1

Grounding Instructions

Caution: This tool must be grounded while in use to protect the operator from electric shock.

In the event of a malfunction or breakdown, grounding provides a path of least resistance for electric current to reduce the risk of electric shock. This tool is equipped with an electric cord having an equipment-grounding conductor and a grounding plug. The plug must be plugged into a matching outlet that is properly installed and grounded in accordance with all local codes and ordinances.

Do not modify the plug provided. If it will not fit the outlet, have the proper outlet installed by a qualified electrician.


Improper connection of the equipment-grounding conductor can result in a risk of electric shock. The conductor, with insulation having an outer surface that is green with or without yellow stripes, is the equipment-grounding conductor. If repair or replacement of the electric cord or plug is necessary, do not connect the equipment-grounding conductor to a live terminal.

Check with a qualified electrician or service personnel if the grounding instructions are not completely understood, or if in doubt as to whether the tool is properly grounded. Use only three wire extension cords that have three-prong grounding plugs and three-pole receptacles that accept the tool's plug.


Repair or replace a damaged or worn cord immediately.

This tool is intended for use on a circuit that has an outlet that looks like the one illustrated in sketch A. The tool has a grounding that looks like the plug illustrated in sketch A. A temporary adapter, which looks like the adapter illustrated in sketches B and C, may be used to connect this plug to a 2-pole receptacle as show in sketch B if a properly until a properly grounded outlet can be installed by a qualified electrician. (This adapter is not permitted in Canada) The green-colored rigid ear, lug, the like, extending from the adapter must be connected to a permanent ground such as a properly grounded outlet box.

This tool is intended for use on a circuit that has an outlet that looks like the one illustrated in sketch D. The tool has a grounding that looks like the plug illustrated in sketch D. Make sure the tool is connected to an outlet having the same configuration as the plug. No adapter is available or should be used with this tool. If the tool must be reconnected for use on a different type of electric circuit, the reconnection should be made by qualified service personnel; and after reconnection, the tool should comply with all local codes and ordinances.



The conversion from 115V to 230V operation must be done by a qualified electrician.






Chart 1 Chart 2

Specifications

Model Number	HVBS-56M 414458
Round @ 90°	5"
Round @ 45°	
Rectangle @ 90°	5"(H) x 5-3/4"(W), and 2"(H) x 6"(W)
Rectangle @ 45°	4-1/2"(H) x 3"(W)
Throat Depth	
Vertical Work Table Size	9-5/8" x 9-1/2"
Vise Swivels	45°
Blade Size	
Blade Wheel Diameter	7-3/8"
Speeds	80, 120, 200 SFPM
Bed Height	
Floor Space Required	
Motor (UL listed)	1/2 HP, 1 Ph, 115/230V, prewired 115V
Net Weight (approx.)	115 lbs.

The specifications in this manual are given as general information and are not binding. Walter Meier (Manufacturing) Inc., reserves the right to effect, at any time and without prior notice, changes or alterations to parts, fittings, and accessory equipment deemed necessary for any reason whatsoever.

Unpacking and Clean-Up

Note: Read and understand the entire manual before attempting setup or operation.

- Remove all contents form the shipping carton.
- 2. Inspect contents for shipping damage and report any damage to your distributor.
- Wipe bed and vise assembly with clean cloth to remove excess oil used to prevent rust.
- 4. Do not discard any packing material until saw has been assembled and is running properly.



Wrench 12/14mm 4mm Angle Hex Wrench

Tools Required for Assembly

- #2 Cross Point Screwdriver
- 6-8" Adjustable Wrench or Wrench Set
- Pliers Regular or Needle Nose
- Ratchet and Sockets will Speed Assembly

Assembly

- With the help of another person turn the saw over so that it rests on the motor and saw bow, Figure 1. Place it on a piece of cardboard, or a surface that will not damage the saw.
- Attach a cross brace (A, Fig. 1) to the motor side of the bed using three 5/16"x1" hex cap bolts, six 5/16" flat washers, and secure with three 5/16" hex nuts. Hint: Tighten the nut (B, Fig. 1) on the end of the bed first followed by the nuts on the sides.
- Attach a leg to the cross brace using four 5/16"x3/4" carriage bolts, four 5/16" flat washers and four 5/16" hex nuts. Use a 12mm wrench to tighten. Repeat for other leg.
- 4. Remove the brace (C, Fig. 1) on the opposite end of the bed and bow using a 10mm wrench.









Fig. 1


5. Attach a cross brace to the opposite end of the bed using three 5/16"x1" hex cap bolts, six 5/16" flat washers, and secure with three 5/16" hex nuts. Tighten the nut on the end of the bed first followed by the nuts on the sides.







8. Slide the axle (A, Fig. 3) through the legs. Place a large flat washer (B, Fig. 3) on both sides of the wheels and place on the axle. Secure wheels with two split pins (C, Fig. 3).



10. Put the handle (A, Fig. 4) through holes in the stand legs opposite of the wheel assembly and secure with split pins.




Fig. 2




Fig. 3




Fig. 4

- 11. Slide pulley cover (A, Fig. 5) around motor shaft and worm gear shaft. Secure with two hex cap screws and washers (B, Fig. 5).
- 12. Lift motor with one hand while the other hand places V-belt (C, Fig.5) on both pulleys.
- 13. Attach the tension bracket (D, Fig. 5) to the saw bow with one 5/16"x3/4" hex head bolt and flat washer (E, Fig. 5).
- 14. Connect the two tension brackets with one 5/16"x3/4" carriage bolt, one 5/16" flat washers and one 5/16" hex nut (F, Fig. 5). Hint: Insert the carriage bolt from the inside so the hex nut is easy to access with a wrench.
- 15. Tension belt by pressing down on the motor while tightening hex nut (F, Fig. 5) until finger pressure on the belt between the two pulleys causes approximately 1/2" deflection. Close pulley cover. Don't over tighten the
- 16. Insert stop rod (A, Fig. 6) into bed and tighten set screw (B, Fig. 6). Slide stock stop (C, Fig. 6) onto rod and tighten set screw (D, Fig. 6) to hold in place.
- 17. Slide handwheel (E, Fig. 6) onto shaft and secure by tightening set screw (F, Fig. 6). Make sure set screw seats on flat portion of shaft.

Vertical Cutting Plate Assembly

Note: These steps are only necessary when using the bandsaw in the vertical mode.

⚠ WARNING

Disconnect the bandsaw from the power source before making any repairs or adjustments!

Failure to comply may cause serious injury!

- 1. Disconnect the bandsaw from the power source.
- 2. Raise the arm to the vertical position and lock in place with lever (A, Fig. 7).
- 3. Loosen bolt (B, Fig. 7) and insert bracket (C, Fig. 7). Tighten bolt just enough to hold the bracket in place.




Fig. 5




Fig. 6




Fig. 7

- 4. Remove two screws (D, Fig. 7) and plate (E, Fig. 7).
- 5. Guide blade through slot in table (A, Fig. 8) and fasten table with two screws (B, Fig. 8).
- 6. Fasten support bracket to underside of table using screw (C, Fig. 8) and hex nut.
- 7. Tighten bolt (B, Fig 7).




Fig. 8

Electrical Connections

↑ WARNING

All electrical connections must be completed by a qualified electrician.

Failure to comply may cause serious injury!

The HVBS-56M bandsaw is rated at 115/230V and comes from the factory prewired 115V.

To switch to 230V operation, follow the wiring diagram found on the inside of the motor junction box. The plug on the end will have to be replaced with a plug that is rated at 230V.

This bandsaw is designed for use on a circuit with an outlet that looks like (A, Fig. 9). The bandsaw has a grounding prong as illustrated in (B, Fig. 9). A temporary adapter (C, Fig. 9) may be used to connect the plug to a two pole receptacle (D, Fig. 9) if a properly grounded outlet is not available. The temporary adapter should only be used until a properly grounded outlet can be installed by a qualified electrician. The green colored lug must be securely fastened to the cover plate screw.

Before hooking up to the power source, be sure the switch is in the off position.




Fig. 9

Changing Blade Speed

- Disconnect the machine from the power source.
- 2. Place saw arm in the horizontal position.
- 3. Loosen tensioning plate hex nut (A, Fig. 10).
- 4. Open pulley cover (B, Fig. 10). Lift motor with one hand while placing the belt (C, Fig. 10) on the desired pulley combination.
- Tension belt by pressing down on the motor while tightening hex nut (A, Fig. 10) until finger pressure on the belt between the two pulleys causes approximately 1/2" deflection. Close pulley cover. Don't over tighten the belt.
- Close pulley cover and connect to power source.

The general rule for band saw blade speed is the harder the material being cut, the slower the blade speed. Reference Figure 11 for a guide to blade speed for a type of material being cut.

Adjusting Blade Guides

- Disconnect machine from the power source.
- 2. Loosen knob (A, Fig. 12) and slide blade guide assembly (B, Fig. 12), as close as, possible without interference to the material being cut. Tighten knob.
- Loosen bolt (C, Fig. 12) and slide blade guide assembly (D, Fig. 12), as close as, possible without interference to the material being cut. Tighten bolt

Adjusting Blade Tension

- Disconnect machine from the power source.
- Open blade cover and observe the position of the blade on the wheel. If the blade is not next to the wheel flange, adjust blade tracking following the steps under "Adjusting Blade Tracking".
- If the blade is next to the wheel flange, loosen the blade guide assembly lock knob and hex head bolt (A & C, Fig. 12) and slide

- the blade guide assemblies as far apart as possible. Lock in place.
- Depress blade. Finger pressure should cause approximately .004" deflection. Turn blade tension knob (B, Fig. 12) until the proper tension is achieved. Re-position guides for cutting material.




Fig. 10

3				
Material	Speed	Motor Pulley	Saw Pulley	
Tool, Stainless, or Alloy Steel, Bearing Bronzes	80 FPM	Small	Large	
Mild Steel, Hard Brass, or Bronze	120 FPM	Medium	Medium	
Soft Brass, Aluminum, or other light materials	200 FPM	Large	Small	

Fig. 11




Fig. 12

Changing Blades

- Disconnect machine from the power source.
- 2. Raise the saw arm to the vertical position and lock in place with lock lever.
- 3. Open blade cover by removing the small knob found on the topside of the bow.
- Remove red blade guards by removing two screws.

⚠ WARNING

It is essential these two guards be installed after the new blade has been fitted. Failure to comply may cause serious injury!

- Release tension on the blade by turning tensioning knob (B, Fig. 12), and remove the blade.
- Place new blade between the blade guide assemblies and around each wheel. Make sure blade teeth are pointing in the proper direction, Figure 13. Tension enough to hold in place.
- 7. Install red blade guards with two screws.
- 8. Tension blade fully, see "Adjusting Blade Tension".
- Place two to three drops of lightweight oil on the blade.
- 10. Connect machine to the power source.
- 11. Run saw and make sure blade is tracking properly, see "Adjusting Blade Tracking".

As a general rule, the thinner the material to be cut, the more teeth per inch on the blade. A minimum of three teeth should be in contact with the material at all times during the cut. If the teeth straddle the material, severe damage can result to the material and the blade.

Adjusting Blade Guide Bearings

- Disconnect machine from the power source.
- Loosen bolt (A, Fig. 14) and adjust assembly so that back roller bearing is approximately .002" - .003" from the back of the blade. Tighten bolt.

- Loosen nut (B, Fig. 14) and turn nut (C, Fig. 14) to adjust eccentric bearing to a clearance of .001". Tighten nut (B, Fig. 14) to lock.
- 4. Connect machine to power source.




Fig. 13




Fig. 14

Adjusting Blade Tracking

⚠ WARNING

Blade tracking adjustment requires running the saw with the back cover open! This adjustment must be completed by qualified persons only!

Failure to comply may cause serious injury!

Blade tracking has been set at the factory and should not need immediate adjustment. If blade tracking should ever require adjustment:

- Confirm that blade tension is set properly.
 To adjust, see section titled " Adjusting Blade Tension".
- 2. Make sure the saw is in its slowest speed, see "Changing Blade Speeds".
- 3. Move saw arm to the vertical position and lock in place with the lock lever.
- Confirm that blade tension is set properly.
 To adjust, see section titled " Adjusting Blade Tension".
- 5. Open blade cover by removing the knob found on the top side of the bow.
- 6. Run saw and observe blade. Blade should run next to but not tightly against wheel flange.
- 7. Loosen bolts (A, Fig. 15).
- 8. Turn set screw (B, Fig. 15) while observing blade tracking on wheel. Turn set screw clockwise to track closer to wheel flange. Turn set screw counter-clockwise to track away from the wheel flange. **Hint:** start with ½ turns on the set screw. The tracking is sensitive.
- 9. Once tracking is set, tighten bolts (A, Fig. 15).

Adjusting Feed Pressure

1. Turn handle (A, Fig. 16) clockwise to decrease cutting pressure and counter-clockwise to increase cutting pressure.

A good indication of proper feed pressure is the color and shape of the cutting chips. If the chips are thin or powdered, increase the feed pressure. If the chips are burned and heavy, decrease the

feed pressure. If they are still burned and heavy, reduce the blade speed. Optimum feed pressure has been set when the chips are curled, silvery, and warm.




Fig. 15




Fig. 16

Blade-Table Squareness

- The band saw blade must be perpendicular to the table to ensure a straight cut. This setting should be checked. Special blade setting gauges can be purchased for this type of inspection; however, it can also be done using more common shop items, as follows.
- 2. First "extend" the surface of the blade by clamping a straight, flat object to the blade. (Figure 16a uses a small, lightweight aluminum ruler.) Use a lightweight clamp.
- 3. Place a square on the table and against the ruler. The square should lie flat against the ruler without a gap.
- 4. If there is a gap, loosen the bolt (Figure 16b) on each blade guide assembly and rotate the blade guide assembly until there is no more gap between the square and the ruler.
- 5. Re-tighten the bolts.
- After making this adjustment, be sure to recheck other blade adjustments as noted in your manual.

Adjusting Automatic Shut-Off

The saw should stop after the cut has been completed:

- If the saw completes the cut and continues to run, adjust the stop tip (A, Fig. 17) down.
- If the saw shuts off before the cut is complete, adjust the stop tip (A, Fig. 17) up.
- If the saw stops cutting but continues to run, adjust the stop bolt (B, fig. 17) down.

The saw is properly adjusted when the saw shuts off just after the blade has finished the cut.

Adjusting the Vise

- 1. To open and close the vise use the handwheel (C, Fig. 17).
- 2. The vise can be adjusted for square and miter cuts. Loosen the hex cap bolts and adjust the vise for the cut.

- 3. Adjust the blade guides so they are as close as possible to the material without interfering.
- 4. There is a scale on the back side of the bed to aid in setting up the vise for 90° cuts or a particular miter. Hint: Always check the vise setup with a combination square, against the blade and vise, so that you can verify the vise setting is correct.




Fig. 16a




Fig. 16b




Fig. 17

Lubrication

Ball bearings on the blade guide assemblies and the blade wheels are permanently sealed and require no lubrication.

Lubricate the vise lead screw as needed with #2 tube grease.

Gear box oil will have to be changed after 90 days of operation. Thereafter, change every six months.

To change the gear box oil:


- Disconnect machine from the power source.
- 2. Place saw arm in the horizontal position.
- 3. Remove screws (A, Fig. 18) from the gear box and remove cover plate and gasket.
- Hold a container under the lower right corner of the gear box with one hand while slowly raising the saw arm with the other. Drain completely.

- 5. Place arm in the horizontal position. Wipe out remaining oil with a rag.
- 6. Fill gear box with approximately 1/2 pint of MOBIL SHC 634.
- 7. Replace gasket and cover. Fasten cover with bolts.




Fig. 18

Breakdown for Bow Assembly



Breakdown for Base Assembly




Parts List for the HVBS-56M Bandsaw

Index No.	Part No.	Deceription	Size	Otre
NO.	NO.	Description	Size	Qty.
		Hex Cap Bolt		
2	TS-0561011	Hex Nut	1/4"	1
3	TS-0680021	Flat Washer	1/4"	4
4	HVBS56M-04	Stand Leg		4
4-1	HVBS56M-04-1	Cross Brace		2
		Washer		
6	HVBS462-006	Cotter Pin	1/8"x1"	4
7	HVBS56M-07	Axle		1
8	TS-0680031	Flat Washer	5/16"	38
		Wheel		
		Washer		
		Hex Cap Bolt		
11-1	HVBS56M-11-1	Carriage Bolt	5/16"x3/4"	16
11-2	TS-0051051	Hex Cap Bolt	5/16"x1"	6
		Hex Nut		
		Adjustable Foot		
		Floor Stand Handle		
		Adjusting Rod		
		Electric Cord		
		Pivoting Rod		
		Support Plate		
		Stock Stop		
20	TC 0270024	Socket Set Screw	F/16"vF/16"	۱۱
		Stock Stop Rod		
		Wire Relief Retainer		
		Hex Cap Bolt		
		Wheel Handle		
		Hand Wheel		
		Toggle Switch Assembly		
		Plastic Cover		
		E-Ring		
		Screw		
		Lead Screw		
		Vise Nut		
		Moveable Vise Plate		
35	TS-0680041	Flat Washer	3/8"x1"	4
		Hex Cap Bolt		
37	HVBS462-037	Bed		1
		Cross Round Head Screw		
39	HVBS462-039	Scale		1
40	HVBS462-040	Electric Cord Clip		1
42	HVBS56M-042	Screw	M4x16	2
43	HVBS462-043	Rubber Ring		1
		Electric Cable		
		Nut Plate		
		Spring Handle Bracket		
		Spring Adjusting Screw		
		Spring		
48	HVBS462-048	Cross Round Head Screw	3/16"x3/8"	4
		Mitering Vise Plate		
		Hex Cap Bolt		
JJ		on our boit		

Index	Part			
No.	No.	Description	Size	Qty.
40	LIV (DO 400 040	Maria de Companya		4
		Mitering Vise Plate		
		Hex Cap Bolt		
		Flat Washer		
		Hex Cap Bolt		
		Hex Cap Screw		
		Pivot Bracket		
		Vertical Cutting Plate		
		Stand for Vertical Cutting Plate		
		Adjustable Bracket LH		
57A	HVBS56M-057A	Adjustable Bracket Assembly LH		1
		Knob		
		Blade Back Safety Cover		
60	HVBS462-060	C-Clip	S10	4
61	BB-6000ZZ	Ball Bearing	6000ZZ	6
		Guide Pivot		
		Center Shaft Assembly (Includes: #60-		
		Centrifugal Guide Pivot		
		Eccentric Shaft Assembly (Includes: #6		
		Bearing Shaft Pin		
		Blade Seat Left		
		Blade Seat Right		
		Adjustable Bracket-RH		
		Adjustable Bracket-Assembly RH		
66 66		Lock Knob		1 1
		Lock Washer		
		Flat Head Machine Screw		
69	HVBS462-069	Bearing Guard		1
		Hex Nut		
		Blade Wheel Drive		
		Bearing Cover		
		Key		
		C-Clip		
75	HVBS462-075	Hex Cap Bolt (w/Washer)	1/4"x1/2"	8
		Switch Cut Off Trip		
		Idle Blade Wheel		
78	TS-0680031	Flat Washer	5/16"	2
79	HVBS462-079	Blade Tension Knob	3/8"	1
80	HVBS462-080	Spring		1
		Saw Bow		
		Washer		
-		Cap Screw		
		Motor Mount Plate		
		Tension Bracket		
		Motor		
		Capacitor Cover (not shown)		
		Capacitor (not shown)		
		Motor Pulley		
		Ball Bearing		
		Bearing Bushing		
		Oil Seal		
		Transmission Wheel Shaft		
		Worm Gear		
		Gear Box Gasket		
93	HVBS462-093	Gear Box Cover		1

Index Part			
No. No.	Description	Size	Qty.
94HVBS462-094	Worm Gear (w/Shaft)		1
	Spring Pin		
96HVBS462-096	Bearing Bushing		1
97TS-0050011	Hex Cap Bolt	1/4"x1/2"	3
98HVBS56M-098	Clamp		2
	Spacer		
	Flat Cross Head Screw		
101HVBS462-101	Worm Gear Pulley		1
	Lock Washer		
	Blade Tension Sliding Plate		
	Socket Set Screw		
	Spring Pin		
	Sliding Plate Draw Block		
	Blade Wheel Shaft		
	Shaft Block		
	Blade Tension Sliding Guide		
	Motor Pulley Cover Assembly		
	Flat Washer		
	V-Belt		
	Blade		
	Flat Washer		
	Hex Nut		
	Wire Plug		
	Hex Screw		
	Bushing		
	Hex Nut		
	Cap Screw		
	Machine Screw		
	Bushing		
	Blade Guard-Right		
	Blade Guard-Left		
	Round Head Screw		
	Star Washer		
	Hex Nut		
	Round Cross Head Screw		
	Blade Speed Label (not shown)		
	I.D. Label (not shown)		
	Warning Label (not shown)		
JIVI-06IVI	Stripe Decal (not shown)		

Wiring Diagram



Notes



427 New Sanford Road LaVergne, Tennessee 37086 Phone: 800-274-6848 www.waltermeier.com