

Lighting Your Life Since 1970

Product Specifications - 89913WT		
Job Name:	Job Type:	
Quantity:	Comments	



89913WT

CounterMax MX-L120DC 13" 3000K 4-LED Under Cabinet

Uses MXInterLink4 accessories. Click here for a complete list of compatible accessories.

inish	Glass/Shade
/hite	Clear

Product Category

Under Cabinet

Lamping	
Number of Bulbs	4
Light Type	LED
Bulb Type	Cree® LED
Max Bulb Wattage	2.44
Max Fixture Wattage	9.76
Rated Life	±50,000 Hours
Rated Lumens	±471
Color Temp	±3,000 K
Bulb(s)	Integrated
Light Up/Down	N/A
Beam Spread	N/A
CRI	85
Photo Cell Included	N/A
Ballast/Driver/Transformer	Yes
Dimmable	Lutron® or Leviton® LED Dimmer

Measurements	
Width	4.00"
Height	1.00"
Length	13.00"
Extension	N/A
Back Plate Width	N/A
Back Plate Height	N/A
HCO	N/A
Min Overall Height	N/A
Max Overall Height	N/A
Hanging Weight	2.31 lbs
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

Shipping	
Carton Weight	2.31 lbs
Carton Width	6"
Carton Height	3"
Carton Length	17"
Carton Cubic Feet	0.16
Master Pack	6
Master Pack Weight	14.96 lbs
Master Pack Width	16.93"
Master Pack Height	6.69"
Master Pack Length	17.32"
Master Cubic Feet	1.14
UPS Shippable	Yes

Certificatio	,,

Finish

W

Certification		Other	
Safety Rating	Dry	UPC Code	783209093263
Energy Star	No	Shades Included	N/A
CA Title 24	No	Crystals Included	N/A
CA Title 20	No	Diffuser Included	N/A
ADA	No	Conversion Kit	N/A
Dark Sky	N/A	Material	N/A

nıı	IVā		

Incandescent Watts	42.82
Fluorescent Watts	9.42

Maxim Lighting International and all designs, logos and images © 2014 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.