



Lighting Your Life Since 1970

## Product Specifications - 4035MREB

Job Name:	Job Type:
Quantity:	Comments:



### 4035MREB

#### Wakefield Cast 1-Light Outdoor Wall Lantern

#### Finish

Empire Bronze

#### Glass/Shade

Marble

#### Product Category

Outdoor Wall Mount

#### Lamping

Number of Bulbs	1
Light Type	Incandescent
Bulb Type	MB
Max Bulb Wattage	150
Max Fixture Wattage	150
Rated Life	±2,500 Hours
Rated Lumens	±1,570
Color Temp	±2,700 K
Bulb(s)	Not Included
Light Up/Down	N/A
Beam Spread	N/A
CRI	N/A
Photo Cell Included	N/A
Ballast/Driver/Transformer	No
Dimmable	Standard

#### Measurements

Width	13.0"
Height	30.0"
Length	N/A
Extension	14"
Back Plate Width	9.0"
Back Plate Height	15.0"
HCO	19.5"
Min Overall Height	N/A
Max Overall Height	N/A
Hanging Weight	15.2 lbs
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

#### Shipping

Carton Weight	15.2 lbs
Carton Width	14"
Carton Height	34"
Carton Length	18"
Carton Cubic Feet	4.86
Master Pack	1
Master Pack Weight	N/A
Master Pack Width	N/A
Master Pack Height	N/A
Master Pack Length	N/A
Master Cubic Feet	N/A
UPS Shippable	Yes

#### Certification

Safety Rating	Wet
Energy Star	No
CA Title 24	No
CA Title 20	No
ADA	No
Dark Sky	N/A

#### Other

UPC Code	783209403505
Shades Included	N/A
Crystals Included	N/A
Diffuser Included	N/A
Conversion Kit	N/A
Material	Die Cast Aluminum

#### Equivalents

Incandescent Watts	N/A
Fluorescent Watts	N/A

Maxim Lighting International and all designs, logos and images © 2013 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.