

## MonoRail Surface Kit 150w



### DESCRIPTION

Includes 8' long hand-bendable MonoRail, two sets of decorative end caps, two rigid standoffs, and a 12 volt 150 watt surface magnetic transformer. Rail drops 4" from ceiling. Add up to three 50 watt elements or up to four 35 or 37 watt elements.

### INSTALLATION

Magnetic transformer mounts to a standard 4" junction box with round plaster ring (provided by electrician) and includes 24" softwire leads.

### DIMMING

Dimmable with a 600 watt low-voltage magnetic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics).

### ORDERING INFORMATION

#### 700MOKTS150 FINISH

- Z ANTIQUE BRONZE
- C CHROME
- S SATIN NICKEL



**TECH LIGHTING®**

7400 Linder Avenue  
Skokie, Illinois 60077

T 847.410.4400  
F 847.410.4500

[www.techlighting.com](http://www.techlighting.com)

700MOKTS150 \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_



©2011 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.