

Kable Lite Surface Transformer-300W 24V Mag



DESCRIPTION

This single-feed surface transformer converts standard 120 volt line-voltage to 24 volts to provide the necessary voltage for powering a Kable Lite system. It can power lamps totaling up to 300 watts. The transformer is concealed inside a decorative housing with a fast-acting secondary circuit breaker that will safely turn off the system should a short occur. Once the short has been removed the breaker can be reset.

INSTALLATION

This product can mount to either a standard 4" square electrical box with round plaster ring or an octagon electrical box (not included).

DIMMING

Dimmable with a 600 watt low-voltage magnetic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics). This surface transformer includes a preinstalled debuzzing dimming coil to reduce audible noise when using a low-voltage dimmer.

OTHER INFORMATION

Black and white finish have chrome feeds. The shortest rigid standoff that can be used with this surface transformer is the 5" rigid post standoff (sold separately). This surface transformer may be plugged in with the addition of a Plug Option, a 16' cord with plug (sold separately). 24 volt transformers require the use of 24 volt lamps.


WEIGHT

12.15lb / 5.51kg

ORDERING INFORMATION

700SRT3024D FINISH

- Z ANTIQUE BRONZE
- B BLACK
- C CHROME
- S SATIN NICKEL
- W WHITE



TECH LIGHTING®

7400 Linder Avenue T 847.410.4400
Skokie, Illinois 60077 F 847.410.4500

www.techlighting.com

700SRT3024D _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____

