





R-F136B-NAZ
(NAZ) Natural Antique Bronze

- PAR36 lamp (35W, WFL included)
- Solid die-cast brass
- 1/2" NPS knuckle with ABS stake included for quick installation
- No socket to ever fail – Uses PAR36 screw terminal lamps
- Large easy to adjust knuckle (can be tightened with a 1/4" hex key)
- Potted knuckle to limit water and insect intrusion into luminaire
- 12 volt UL 1838 listed luminaire is safe for wet locations up to 50W
- Natural antique bronze patina finish (NAZ), standard
- Honeycomb anti-glare filter included
- Adjustable shroud is lockable with hex key (included)
- 25' of 16 AWG SPT-2W cable and direct-bury wire connectors included
- Optional cast brass or powder coated cast aluminum stake
- Requires low voltage power supply, ordered separately



Solid Brass knuckle is easily adjustable and may be secured with an hex key. The knuckle is potted to limit moisture and insect intrusion.



R-A3A



R-A3B

OPTIONAL PARTS

MODEL NO	DESCRIPTION
R-A3A	Aluminum Stake Powder Coat
R-A3B	Natural Solid Brass Stake

Model	Material	Lamp	Natural Finishes	Powder Coat
R-F136	B Solid Brass	PAR36 2000 hr, 35W WFL included	NAZ NAP	PAB PBZ
			NAR NAS	PDV POC
			NOC UFB	PRI PSD
			NFC	PTB PWB
				PTW

R-F136B - NAZ

MODEL NO	MATERIAL	FINISH
	B=Brass	Natural Antique Bronze

*We reserve the right to change specifications without notice.