

| ELEMENT 2" | | | | | |
|----------------|----------------|-----------------------|---------------------|--------------------------------|-----------------------------------------------------------------------------------|
| MANUFACTURER | DIMMER TYPE | PART NUMBER | FIXTURES PER DIMMER | MEASURED LIGHTING OUTPUT RANGE | COMMENTS |
| Crestron | Dimming Module | CLS-C6 | Consult Dimmer Co. | 100% - 13% | |
| Crestron | Dimming Module | CLS-C6EX | Consult Dimmer Co. | 100% - 13% | |
| Crestron | Dimming Module | CLS-C6M | Consult Dimmer Co. | 100% - 13% | |
| Crestron | Dimming Module | CLS-C6MEX | Consult Dimmer Co. | 100% - 13% | |
| Crestron | Dimming Module | CLS-C6MRF | Consult Dimmer Co. | 100% - 13% | |
| Crestron | Dimming Module | CLS-C6RF | Consult Dimmer Co. | 100% - 13% | |
| Crestron | Dimming Module | CLS-EXP-DIM | Consult Dimmer Co. | 100% - 17% | 12% low-end on 277V |
| Crestron | Dimming Module | CLS-EXP-DIMU | Consult Dimmer Co. | N/A | Not recommended 120v, 100%-8% on 277v |
| Crestron | Dimming Module | CLW-DELVEX-277-P | Consult Dimmer Co. | 100% - 5% | 277v only |
| Crestron | Dimming Module | CLW-DELVEX-E | Consult Dimmer Co. | 100% - 12% | |
| Crestron | Dimming Module | CLW-DELVEX-P | Consult Dimmer Co. | 100% - 12% | |
| Crestron | Dimming Module | CLW-DIMEX-E | N/A | N/A | Not recommended- some flicker |
| Crestron | Dimming Module | CLW-DIMEX-P | N/A | N/A | Not recommended- some flicker |
| Crestron | Dimming Module | CLW-DIMSWEX-E | N/A | N/A | Not recommended- some flicker |
| Crestron | Dimming Module | CLW-DIMSWEX-P | N/A | N/A | Not recommended- some flicker |
| Crestron | Dimming Module | CLX-1DELV4 | Consult Dimmer Co. | 100% - 16% | |
| Crestron | Dimming Module | CLX-1DIM4 | Consult Dimmer Co. | 100% - 20% | May require firmware, consult Crestron |
| Crestron | Dimming Module | CLX-1DIM8 | Consult Dimmer Co. | 100% - 20% | May require firmware, consult Crestron |
| Crestron | Dimming Module | CLX-2DIM2 | Consult Dimmer Co. | 100% - 20% | May require firmware, consult Crestron |
| Crestron | Dimming Module | CLX-2DIM8 | Consult Dimmer Co. | 100% - 20% | May require firmware, consult Crestron |
| Crestron | Dimming Module | DIN-1DIM4 | Consult Dimmer Co. | 100% - 12% | 100% - 8% ON 277V |
| Crestron | Dimming Module | DIN-1DIMU4 | Consult Dimmer Co. | 100% - 14% | |
| Crestron | Dimming Module | GLX-DIM6 | Consult Dimmer Co. | 100% - 5% | 100% - 7% ON 277V |
| Crestron | Dimming Module | GLXX-2DIM8 | Consult Dimmer Co. | 100% - 6% | 100% - 7% ON 277V |
| Crestron | Dimming Module | P-DIMEX | N/A | N/A | Not recommended- some flicker |
| Forbes & Lomax | Incandescent | 600 Watt Incandescent | 1 - 6 | 96% - 15% | Do not exceed load listed |
| Leviton | MLV | Model 6613 | Not Recommended | Not Recommended | Limited dimming range, not recommended |
| Leviton | ELV | Model 6615 | 1 - 18 | 96% - 20% | |
| Leviton | Incandescent | Model 6633 | 1 - 7 | 96% - 3% | Single fixture will not power at lowest end of dimming range |
| Leviton | UNIV | Model 6672 | 1 - 12 | 96% - 25% | |
| Leviton | UNIV | Model 6674/IPL06 | 1 - 12 | 96% - 4% | |
| Leviton | ELV | Model IPE04 | 1 - 18 | 96% - 10% | |
| Leviton | Incandescent | Model IPI06 | 1 - 7 | 96% - 15% | |
| Leviton | MLV | Model IPM06 | Not Recommended | Not Recommended | Limited dimming range, not recommended |
| Leviton | UNIV | Model IPSD6/IPVD6 | Not Recommended | Not Recommended | Limited dimming range, not recommended |
| Leviton | Incandescent | Model VP106 | 1 - 7 | 96% - 6% | |
| Leviton | ELV | Model VPE04 | 1 - 18 | 96% - 18% | |
| Leviton | MLV | Model VPM06 | 1 - 12 | 96% - 5% | |
| Leviton | Incandescent | Model VR106 | Not Recommended | Not Recommended | Limited dimming range, not recommended |
| Leviton | ELV | Model VRE04 | 1 - 18 | 96% - 10% | |
| Leviton | MLV | Model VRM10 | 1 - 12 | 96% - 5% | |
| Lutron | Incandescent | DV-600P-WH | 1 - 3 | 98% - 1% | |
| Lutron | Incandescent | DVCL-153P-WH | Not Recommended | Not Recommended | Buzzing |
| Lutron | ELV | DVELV-303P | 1 - 18 | 97% - 4% | |
| Lutron | ELV | HQRD-6NA | 1-10 | 96%-2% | |
| Lutron | Dimming Module | HW/LP-RPM-4A-120 | 1 - 10 | 100% - 15% | High and low-end trim required |
| Lutron | Dimming Module | HW/LP-RPM-4U-120 | 1 - 10 | 100% - 13% | High and low-end trim required |
| Lutron | Incandescent | MA-600-WH | Not Recommended | Not Recommended | Flicker at low end |
| Lutron | ELV | MRF2-6ELV-120-WH | 1 - 18 | 98% - 2% | |
| Lutron | ELV | NTELV-600-WH | 1 - 18 | 98% - 8% | |
| Lutron | ELV | NVELV-600-WH | 1 - 18 | 94% - 10% | |
| Lutron | ELV | SELV-600-WH | 1 - 18 | 94% - 4% | |
| Vantage | Dimming Module | EDIMMOD | Min 1 | 96% - 10% | Consult dimmer company for max fixtures per dimmer. Recommend PWM, reverse phase. |
| Vantage | Dimming Module | RDR4 | Min 2 | 100% - 2% | Consult dimmer company for max fixtures per dimmer. Recommend PWM, reverse phase. |
| Vantage | Dimming Module | SDM12-EM | Min 2 | 95% - 7% | Consult dimmer company for max fixtures per dimmer. Recommend PWM, reverse phase. |

ELEMENT 2" Hi Lume Driver- 2 wire dimming only*

| MANUFACTURER | DIMMER TYPE | PART NUMBER | FIXTURES PER DIMMER | MEASURED LIGHTING OUTPUT RANGE | COMMENTS |
|--------------|---------------------------------------------------------------|--------------------------------|---------------------|--------------------------------|---------------------------------------------|
| Lutron | GRAFIK Eye 3000 | GRX-3100, GRX-3500 | 1-10 (per output) | 100-1% | Set load type before adjusting low-end trim |
| Lutron | HomeWorks QS 1000W(LED) | HQRD-10ND | 1-13 | 100-1% | Set load type before adjusting low-end trim |
| Lutron | HomeWorks QS adaptive dimmer | HQRD-6NA | 1-8 | 100-1% | Set load type before adjusting low-end trim |
| Lutron | HomeWorks QS 600W (LED) | HQRD-6ND | 1-8 | 100-1% | Set load type before adjusting low-end trim |
| Lutron | HomeWorks QS WPM (LED) | HQRJ-WPM-6D-120 | 1-10 (per output) | 100-1% | Set load type before adjusting low-end trim |
| Lutron | HomeWorks 1000W dimmer | HRD-10ND, HWD-10ND | 1-13 | 100-1% | |
| Lutron | HomeWorks 600W dimmer | HRD-6ND | 1-8 | 100-1% | |
| Lutron | HomeWorks WPM | HWI-WPM-6D-120 | 1-10 (per output) | 100-1% | |
| Lutron | RPM-4A module (LCP, HomeWorks, GRAFIK Systems, Quantum) (LED) | HW-RPM-4A-120 LP-RPM-4A-120 | 1-13 (per output) | 100-1% | Set load type before adjusting low-end trim |
| Lutron | RPM-4U module (LCP, HomeWorks, GRAFIK Systems, Quantum) (LED) | HW-RPM-4U-120 LP-RPM-4U-120 | 1-10 (per output) | 100-1% | Set load type before adjusting low-end trim |
| Lutron | Maestro Wireless | MRF2-6nd-120 | 1-8 | 100-1% | Do Not Use, Low Level Humming |
| Lutron | Nova T | NTLV-600-CPN0199 | 1-8 | 100-1% | |
| Lutron | GRAFIK Eye QS | QSGR, QSGRJ | 1-10 (per output) | 100-1% | Set load type before adjusting low-end trim |
| Lutron | RadioRA 1000W | RA-10ND | 1-13 | 100-1% | |
| Lutron | RadioRA 600W | RA-6ND | 1-8 | 100-1% | |
| Lutron | RadioRa 2 1000W | RRD-10ND | 1-13 | 100-1% | |
| Lutron | Radio Ra 2 adaptive dimmer | RRD-6NA | 1-8 | 100-1% | |
| Lutron | Stanza | SZ-6ND | 1-8 | 100-1% | |

*NOTE: Two wire dimming only, not valid for 5 wire dimming. Contact Lutron tech support for deganging rules when using wallbox controls on the Hi-lume A-Series LED driver. Low-end trim may need to be adjusted to achieve 1% dimming. For information on low-end trim adjustment, consult installation instructions.

ELEMENT 3"

| MANUFACTURER | DIMMER TYPE | PART NUMBER | FIXTURES PER DIMMER | MEASURED LIGHTING OUTPUT RANGE | COMMENTS |
|----------------|----------------|-----------------------|---------------------|--------------------------------|-----------------------------------------------------------------------------------|
| Crestron | Dimming Module | CLS-C6 | Consult Dimmer Co. | 100% - 13% | |
| Crestron | Dimming Module | CLS-C6EX | Consult Dimmer Co. | 100% - 13% | |
| Crestron | Dimming Module | CLS-C6M | Consult Dimmer Co. | 100% - 13% | |
| Crestron | Dimming Module | CLS-C6MEX | Consult Dimmer Co. | 100% - 13% | |
| Crestron | Dimming Module | CLS-C6MRF | Consult Dimmer Co. | 100% - 13% | |
| Crestron | Dimming Module | CLS-C6RF | Consult Dimmer Co. | 100% - 13% | |
| Crestron | Dimming Module | CLS-EXP-DIM | Consult Dimmer Co. | 100% - 17% | 12% low-end on 277V |
| Crestron | Dimming Module | CLS-EXP-DIMU | Consult Dimmer Co. | N/A | Not recommended 120v, 100%-8% on 277v |
| Crestron | Dimming Module | CLW-DELVEX-277-P | Consult Dimmer Co. | 100% - 5% | 277v only |
| Crestron | Dimming Module | CLW-DELVEX-E | Consult Dimmer Co. | 100% - 12% | |
| Crestron | Dimming Module | CLW-DELVEX-P | Consult Dimmer Co. | 100% - 12% | |
| Crestron | Dimming Module | CLW-DIMEX-E | N/A | N/A | Not recommended- some flicker |
| Crestron | Dimming Module | CLW-DIMEX-P | N/A | N/A | Not recommended- some flicker |
| Crestron | Dimming Module | CLW-DIMSWEX-E | N/A | N/A | Not recommended- some flicker |
| Crestron | Dimming Module | CLW-DIMSWEX-P | N/A | N/A | Not recommended- some flicker |
| Crestron | Dimming Module | CLX-1DELV4 | Consult Dimmer Co. | 100% - 16% | |
| Crestron | Dimming Module | CLX-1DIM4 | Consult Dimmer Co. | 100% - 20% | May require firmware, consult Crestron |
| Crestron | Dimming Module | CLX-1DIM8 | Consult Dimmer Co. | 100% - 20% | May require firmware, consult Crestron |
| Crestron | Dimming Module | CLX-2DIM2 | Consult Dimmer Co. | 100% - 20% | May require firmware, consult Crestron |
| Crestron | Dimming Module | CLX-2DIM8 | Consult Dimmer Co. | 100% - 20% | May require firmware, consult Crestron |
| Crestron | Dimming Module | DIN-1DIM4 | Consult Dimmer Co. | 100% - 12% | 100% - 8% ON 277V |
| Crestron | Dimming Module | DIN-1DIMU4 | Consult Dimmer Co. | 100% - 14% | |
| Crestron | Dimming Module | GLX-DIM6 | Consult Dimmer Co. | 100% - 5% | 100% - 7% ON 277V |
| Crestron | Dimming Module | GLXX-2DIM8 | Consult Dimmer Co. | 100% - 6% | 100% - 7% ON 277V |
| Crestron | Dimming Module | P-DIMEX | N/A | N/A | Not recommended- some flicker |
| Forbes & Lomax | Incandescent | 600 Watt Incandescent | 1 - 6 | 96% - 15% | Do not exceed load listed |
| Leviton | MLV | Model 6613 | Not Recommended | Not Recommended | Limited dimming range, not recommended |
| Leviton | ELV | Model 6615 | 1 - 18 | 96% - 20% | |
| Leviton | Incandescent | Model 6633 | 1 - 7 | 96% - 3% | Single fixture will not power at lowest end of dimming range |
| Leviton | UNIV | Model 6672 | 1 - 12 | 96% - 25% | |
| Leviton | UNIV | Model 6674/IPL06 | 1 - 12 | 96% - 4% | |
| Leviton | ELV | Model IPE04 | 1 - 18 | 96% - 10% | |
| Leviton | Incandescent | Model IPI06 | 1 - 7 | 96% - 15% | |
| Leviton | MLV | Model IPM06 | Not Recommended | Not Recommended | Limited dimming range, not recommended |
| Leviton | UNIV | Model IPSD6/IPVD6 | Not Recommended | Not Recommended | Limited dimming range, not recommended |
| Leviton | Incandescent | Model VP106 | 1 - 7 | 96% - 6% | |
| Leviton | ELV | Model VPE04 | 1 - 18 | 96% - 18% | |
| Leviton | MLV | Model VPM06 | 1 - 12 | 96% - 5% | |
| Leviton | Incandescent | Model VR106 | Not Recommended | Not Recommended | Limited dimming range, not recommended |
| Leviton | ELV | Model VRE04 | 1 - 18 | 96% - 10% | |
| Leviton | MLV | Model VRM10 | 1 - 12 | 96% - 5% | |
| Lutron | Incandescent | DV-600P-WH | 1 - 3 | 98% - 1% | |
| Lutron | Incandescent | DVCL-153P-WH | Not Recommended | Not Recommended | Buzzing |
| Lutron | ELV | DVELV-303P | 1 - 18 | 97% - 4% | |
| Lutron | ELV | HQRD-6NA | 1-10 | 96%-2% | |
| Lutron | Dimming Module | HW/LP-RPM-4A-120 | 1 - 10 | 100% - 15% | High and low-end trim required |
| Lutron | Dimming Module | HW/LP-RPM-4U-120 | 1 - 10 | 100% - 13% | High and low-end trim required |
| Lutron | Incandescent | MA-600-WH | Not Recommended | Not Recommended | Flicker at low end |
| Lutron | ELV | MRF2-6ELV-120-WH | 1 - 18 | 98% - 2% | |
| Lutron | ELV | NTELV-600-WH | 1 - 18 | 98% - 8% | |
| Lutron | ELV | NVELV-600-WH | 1 - 18 | 94% - 10% | |
| Lutron | ELV | SELV-600-WH | 1 - 18 | 94% - 4% | |
| Vantage | Dimming Module | EDIMMOD | Min 1 | 96% - 10% | Consult dimmer company for max fixtures per dimmer. Recommend PWM, reverse phase. |
| Vantage | Dimming Module | RDR4 | Min 2 | 100% - 2% | Consult dimmer company for max fixtures per dimmer. Recommend PWM, reverse phase. |
| Vantage | Dimming Module | SDM12-EM | Min 2 | 95% - 7% | Consult dimmer company for max fixtures per dimmer. Recommend PWM, reverse phase. |

ELEMENT 3" Hi Lume Driver- 2 wire dimming only*

| MANUFACTURER | DIMMER TYPE | PART NUMBER | FIXTURES | MEASURED LIGHTING | COMMENTS |
|--------------|-------------|-------------|----------|-------------------|----------|
|--------------|-------------|-------------|----------|-------------------|----------|

| MANUFACTURER | DIMMER TYPE | PART NUMBER | PER DIMMER | OUTPUT RANGE | COMMENTS |
|--------------|---------------------------------------------------------------|--------------------------------|-------------------|--------------|---------------------------------------------|
| Lutron | GRAFIK Eye 3000 | GRX-3100, GRX-3500 | 1-10 (per output) | 100-1% | Set load type before adjusting low-end trim |
| Lutron | HomeWorks QS 1000W(LED) | HQRD-10ND | 1-13 | 100-1% | Set load type before adjusting low-end trim |
| Lutron | HomeWorks QS adaptive dimmer | HQRD-6NA | 1-8 | 100-1% | Set load type before adjusting low-end trim |
| Lutron | HomeWorks QS 600W (LED) | HQRD-6ND | 1-8 | 100-1% | Set load type before adjusting low-end trim |
| Lutron | HomeWorks QS WPM (LED) | HQRJ-WPM-6D-120 | 1-10 (per output) | 100-1% | Set load type before adjusting low-end trim |
| Lutron | HomeWorks 1000W dimmer | HRD-10ND, HWD-10ND | 1-13 | 100-1% | |
| Lutron | HomeWorks 600W dimmer | HRD-6ND | 1-8 | 100-1% | |
| Lutron | HomeWorks WPM | HWI-WPM-6D-120 | 1-10 (per output) | 100-1% | |
| Lutron | RPM-4A module (LCP, HomeWorks, GRAFIK Systems, Quantum) (LED) | HW-RPM-4A-120 LP-RPM-4A-120 | 1-13 (per output) | 100-1% | Set load type before adjusting low-end trim |
| Lutron | RPM-4U module (LCP, HomeWorks, GRAFIK Systems, Quantum) (LED) | HW-RPM-4U-120 LP-RPM-4U-120 | 1-10 (per output) | 100-1% | Set load type before adjusting low-end trim |
| Lutron | Maestro Wireless | MRF2-6nd-120 | 1-8 | 100-1% | Do Not Use, Low Level Humming |
| Lutron | Nova T | NTLV-600-CPN0199 | 1-8 | 100-1% | |
| Lutron | GRAFIK Eye QS | QSGR, QSGRJ | 1-10 (per output) | 100-1% | Set load type before adjusting low-end trim |
| Lutron | RadioRA 1000W | RA-10ND | 1-13 | 100-1% | |
| Lutron | RadioRA 600W | RA-6ND | 1-8 | 100-1% | |
| Lutron | RadioRa 2 1000W | RRD-10ND | 1-13 | 100-1% | |
| Lutron | Radio Ra 2 adaptive dimmer | RRD-6NA | 1-8 | 100-1% | |
| Lutron | Stanza | SZ-6ND | 1-8 | 100-1% | |

*NOTE: Two wire dimming only, not valid for 5 wire dimming. Contact Lutron tech support for degangng rules when using wallbox controls on the Hi-lume A-Series LED driver. Low-end trim may need to be adjusted to achieve 1% dimming. For information on low-end trim adjustment, consult installation instructions.

ELEMENT 4"

| MANUFACTURER | DIMMER TYPE | PART NUMBER | FIXTURES PER DIMMER | MEASURED LIGHTING OUTPUT RANGE | COMMENTS |
|--------------|--------------|------------------|---------------------|--------------------------------|--------------------|
| Lutron | Incandescent | DV-600P-WH | 1 - 2 | 98% - 5% | |
| Lutron | ELV | DVCL-153P-WH | Not Recommended | Not Recommended | Buzzing |
| Lutron | ELV | DVELV-303P | 1 - 12 | 95% - 10% | |
| Lutron | ELV | HQRD-6NA | 1-10 | 96%-2% | |
| Lutron | Incandescent | MA-600-WH | Not Recommended | Not Recommended | Flicker at low end |
| Lutron | ELV | MRF2-6ELV-120-WH | 1 - 12 | 96% - 2% | |
| Lutron | ELV | NTLV-600-WH | 1 - 12 | 96% - 15% | |
| Lutron | ELV | NVELV-600-WH | 1 - 12 | 94% - 20% | |
| Lutron | ELV | SELV-600-WH | 1 - 12 | 94% - 10% | |

ELEMENT 6" LED Adjustable Retrofit

| MANUFACTURER | DIMMER TYPE | PART NUMBER | FIXTURES PER DIMMER | MEASURED LIGHTING OUTPUT RANGE | COMMENTS |
|----------------|--------------|-------------|---------------------|--------------------------------|-------------------------------------------------------------------------------|
| Cooper | Incandescent | DAL06P | 1-20 | 100% - 1% | Light flickers at low end of dimming. |
| Cooper | Incandescent | DLC03P | 1-20 | 100% - 1% | Light flickers at low end of dimming. |
| Cooper | Incandescent | SLC03P | 1-20 | 100% - 0% | Light flickers at low end of dimming. |
| Forbes & Lomax | Incandescent | FLR603P | 4-20 | 100% - 7% | Light flickers at low end of dimming. |
| Legrand | Incandescent | H703PTVW | 1-25 | 100% - 10% | Light flickers at low end of dimming. |
| Legrand | Incandescent | HCL453PW | 1-25 | 100% - 12% | Light flickers at low end of dimming. |
| Leviton | Incandescent | 6161 | 1-21 | 100% - 13% | Light flickers at low end of dimming. |
| Leviton | Incandescent | 6631 | 1-25 | 100% - 0% | Light flickers at low end of dimming. |
| Leviton | Incandescent | 6633-P | 1-25 | 100% - 1% | Light flickers at low end of dimming. |
| Leviton | Incandescent | 6673-10W | 1-15 | 100% - 8% | Light flickers at low end of dimming. |
| Leviton | Incandescent | 6683-IW | 1-25 | 100% - 2% | Light flickers at low end of dimming. |
| Leviton | ELV | IPE04 | 1-16 | 100% - 4% | Recommended |
| Leviton | Incandescent | IPI06-1LZ | 1-25 | 100% - 0% | Light flickers at low end of dimming. |
| Leviton | ELV | VPE06 | 1-25 | 100% - 6% | Recommended |
| Leviton | Incandescent | VPI06 | Doesn't work | Doesn't work | Doesn't work |
| Lightolier | Incandescent | ZP260QEW | Consult Dimmer Co. | 99%-4% | Light flickers at low end of dimming. |
| Lutron | Incandescent | AY-600P | 1-26 | 100% - 12% | Light flickers at low end of dimming. |
| Lutron | Incandescent | CT103P | 1-40 | 100% - 7% | Light flickers at low end of dimming. |
| Lutron | CL | CTCL-153P | 1-10 | 98% - 25% | Low level flicker is better than incandescent dimmers but not as good as ELV. |
| Lutron | Incandescent | D-600P | 1-25 | 99%-0% | Light flickers at low end of dimming. |
| Lutron | Incandescent | DV-600P | 1-25 | 100% - 5% | Light flickers at low end of dimming. |
| Lutron | Incandescent | DVCL-153P | 1-10 | 100% - 5% | Light flickers at low end of dimming. |
| Lutron | CL | DVCL-153P | 1-10 | 98% - 17% | Low level flicker is better than incandescent dimmers but not as good as ELV. |

| | | | | | |
|--------|--------------|---------------|------|------------|-------------------------------------------------------------------------------|
| Lutron | ELV | DVELV-300P | 3-12 | 94% - 7% | Recommended |
| Lutron | ELV | DVELV-303P | 3-12 | 94% - 7% | Recommended |
| Lutron | ELV | FAELV-500 | 3-21 | 100% - 8% | Recommended |
| Lutron | Incandescent | GL-600P | 1-25 | 100% - 7% | Light flickers at low end of dimming. |
| Lutron | ELV | HQRD-6NA | 3-25 | 97% - 1% | Recommended |
| Lutron | Incandescent | LG-600P | 1-25 | 99% - 5% | Light flickers at low end of dimming. |
| Lutron | CL | LGCL-153P | 1-10 | 97%-8% | Low level flicker is better than incandescent dimmers but not as good as ELV. |
| Lutron | Incandescent | MA-600 | 3-25 | 99% -2% | Light flickers at low end of dimming. |
| Lutron | CL | MACL-153M | 1-10 | 94% - 9% | Low level flicker is better than incandescent dimmers but not as good as ELV. |
| Lutron | ELV | MAELV-600 | 3-25 | 100% - 1% | Recommended |
| Lutron | Incandescent | MAW-600 | 3-25 | 99% -2% | Light flickers at low end of dimming. |
| Lutron | Incandescent | MAW-600 | 3-25 | 99% -2% | Light flickers at low end of dimming. |
| Lutron | ELV | MRF2-6ELV-120 | 3-25 | 97% - 1% | Recommended |
| Lutron | ELV | NTELV-600 | 3-25 | 96-10% | Recommended |
| Lutron | ELV | NTELV-600 | 3-25 | 96-10% | Recommended |
| Lutron | ELV | RRD-6NA | 1-25 | 98% - 1% | Recommended |
| Lutron | Incandescent | S600P | 1-25 | 100% - 3% | Light flickers at low end of dimming. |
| Lutron | Incandescent | S600P | 1-25 | 100% - 3% | Light flickers at low end of dimming. |
| Lutron | Incandescent | S-600P | 1-25 | 98% - 8% | Light flickers at low end of dimming. |
| Lutron | Incandescent | S-603PG | 3-25 | 86% - 6% | Light flickers at low end of dimming. |
| Lutron | CL | SCL-153P | 1-10 | 99% - 6% | Low level flicker is better than incandescent dimmers but not as good as ELV. |
| Lutron | ELV | SELV-300P | 3-12 | 93% - 7% | Recommended |
| Lutron | Incandescent | TG-600P | 1-25 | 100% - 13% | Light flickers at low end of dimming. |
| Lutron | CL | TGCL-153P | 1-10 | 100% - 1% | Low level flicker is better than incandescent dimmers but not as good as ELV. |
| Lutron | CL | TGCL-153P | 1-10 | 98% - 1% | Low level flicker is better than incandescent dimmers but not as good as ELV. |

ELEMENT Reflections 12-inch

| MANUFACTURER | DIMMER TYPE | PART NUMBER | FIXTURES PER DIMMER | MEASURED LIGHTING OUTPUT RANGE | COMMENTS |
|----------------|-------------|----------------|---------------------|--------------------------------|-----------------------|
| Forbes & Lomax | Triac | FLR603P | Consult Dimmer Co. | 100-13% | |
| Insteon | ELV | 2477D | Consult Dimmer Co. | 100-20% | |
| Legrand | C*L | HCL45-3PW | Consult Dimmer Co. | 100-16% | |
| Lutron | Triac | AY-600P-WH | Consult Dimmer Co. | 100-18% | |
| Lutron | Triac | D-600P-WH | Consult Dimmer Co. | 100-7% | |
| Lutron | C*L | DSL06-1LZ | Consult Dimmer Co. | 100-10% | |
| Lutron | Triac | DV-600P | Consult Dimmer Co. | 100-12% | |
| Lutron | C*L | DVCL-153P | Consult Dimmer Co. | 100-2% | |
| Lutron | ELV | DVELV-300P | Consult Dimmer Co. | 100-8% | |
| Lutron | Triac | GL-600P-WH | Consult Dimmer Co. | 100-12% | |
| Lutron | ELV | HQRD-6NA | Consult Dimmer Co. | 100-3% | |
| Lutron | Triac | MA-600-WH | Consult Dimmer Co. | 100-5% | |
| Lutron | C*L | MACL-153M | Consult Dimmer Co. | 100-9% | |
| Lutron | ELV | MAELV-600 | Consult Dimmer Co. | 100-3% | |
| Lutron | ELV | MRF-2-6ELV-120 | Consult Dimmer Co. | 100-3% | |
| Lutron | ELV | NTELV-500 | Consult Dimmer Co. | 100-12% | |
| Lutron | C*L | PD-6WCL | Consult Dimmer Co. | 100-0.5% | |
| Lutron | ELV | RRD-6NA | Consult Dimmer Co. | 100-3% | |
| Lutron | ELV | RRD-6NA | Consult Dimmer Co. | 100-2% | pop-on |
| Lutron | Triac | S-600P | Consult Dimmer Co. | 100-13% | |
| Lutron | ELV | SELV-300P | Consult Dimmer Co. | 100-8% | |
| Lutron | C*L | TGCL-153P | Consult Dimmer Co. | 100-20% | slight flicker at dim |

ELEMENT Reflections 5-inch

| MANUFACTURER | DIMMER TYPE | PART NUMBER | FIXTURES PER DIMMER | MEASURED LIGHTING OUTPUT RANGE | COMMENTS |
|----------------|-------------|-------------|---------------------|--------------------------------|------------------|
| Forbes & Lomax | Triac | FLR603P | Consult Dimmer Co. | 100-12% | pop-on |
| Insteon | ELV | 2477D | Consult Dimmer Co. | 100-2% | |
| Legrand | C*L | HCL45-3PW | Consult Dimmer Co. | 100-15% | pop-on |
| Lutron | Triac | AY-600P-WH | Consult Dimmer Co. | 100-17% | |
| Lutron | Triac | D-600P-WH | Consult Dimmer Co. | 100-3% | flicker below 3% |
| Lutron | C*L | DSL06-1LZ | Consult Dimmer Co. | 100-8% | |

| | | | | | |
|--------|-------|----------------|--------------------|----------|-----------------|
| Lutron | Triac | DV-600P | Consult Dimmer Co. | 100-11% | |
| Lutron | C*L | DVCL-153P | Consult Dimmer Co. | 100-1% | |
| Lutron | ELV | DVELV-300P | Consult Dimmer | 100-7% | |
| Lutron | Triac | GL-600P-WH | Consult Dimmer Co. | 100-11% | |
| Lutron | ELV | HQRD-6NA | Consult Dimmer Co. | 100-2% | pop-on |
| Lutron | Triac | MA-600-WH | N/A | Flicker | Not recommended |
| Lutron | C*L | MACL-153M | Consult Dimmer Co. | 100-10% | |
| Lutron | ELV | MAELV-600 | Consult Dimmer Co. | 100-2% | pop-on |
| Lutron | ELV | MRF-2-6ELV-120 | Consult Dimmer Co. | 100-2% | pop-on |
| Lutron | ELV | NTELV-500 | Consult Dimmer Co. | 100-12% | |
| Lutron | C*L | PD-6WCL | Consult Dimmer Co. | 100-0.5% | |
| Lutron | Triac | S-600P | Consult Dimmer Co. | 100-13% | |
| Lutron | ELV | SELV-300P | Consult Dimmer Co. | 100-7% | |
| Lutron | C*L | TGCL-153P | Consult Dimmer Co. | 100-19% | |

ELEMENT Reflections 8-inch

| MANUFACTURER | DIMMER TYPE | PART NUMBER | FIXTURES PER DIMMER | MEASURED LIGHTING OUTPUT RANGE | COMMENTS |
|----------------|-------------|----------------|---------------------|--------------------------------|--------------------------------------------|
| Forbes & Lomax | Triac | FLR603P | Consult Dimmer Co. | 100-14% | |
| Insteon | ELV | 2477D | Consult Dimmer Co. | 100-3% | |
| Legrand | C*L | HCL45-3PW | Consult Dimmer Co. | 100-17% | pop-on |
| Lutron | Triac | AY-600P-WH | Consult Dimmer Co. | 100-23% | |
| Lutron | Triac | D-600P-WH | Consult Dimmer Co. | 100-4% | pop-on |
| Lutron | C*L | DSL06-1LZ | Consult Dimmer Co. | 100-10% | |
| Lutron | Triac | DV-600P | Consult Dimmer Co. | 100-13% | |
| Lutron | C*L | DVCL-153P | Consult Dimmer Co. | 100-2% | flash on when turned on from dimmest level |
| Lutron | ELV | DVELV-300P | Consult Dimmer Co. | 100-8% | |
| Lutron | Triac | GL-600P-WH | Consult Dimmer Co. | 100-15% | |
| Lutron | ELV | HQRD-6NA | Consult Dimmer Co. | 100-3% | |
| Lutron | Triac | MA-600-WH | Consult Dimmer Co. | 100-6% | |
| Lutron | C*L | MACL-153M | Consult Dimmer Co. | 100-12% | |
| Lutron | ELV | MAELV-600 | Consult Dimmer Co. | 100-3% | |
| Lutron | ELV | MRF-2-6ELV-120 | Consult Dimmer Co. | 100-3% | |
| Lutron | ELV | NTELV-500 | Consult Dimmer Co. | 100-13% | |
| Lutron | C*L | PD-6WCL | Consult Dimmer Co. | 100-0.5% | |
| Lutron | ELV | RRD-6NA | Consult Dimmer Co. | 100-3% | |
| Lutron | Triac | S-600P | Consult Dimmer Co. | 100-16% | |
| Lutron | ELV | SELV-300P | Consult Dimmer Co. | 100-9% | |
| Lutron | C*L | TGCL-153P | Consult Dimmer Co. | 100-21% | |

ENTRA

| MANUFACTURER | DIMMER TYPE | PART NUMBER | FIXTURES PER DIMMER | MEASURED LIGHTING OUTPUT RANGE | COMMENTS |
|----------------|-------------|---------------|---------------------|--------------------------------|----------|
| Forbes & Lomax | Triac | FLR603P | Consult Dimmer Co. | 100-6% | |
| Insteon | ELV | 2477D | Consult Dimmer Co. | 100-14% | |
| Legrand | U | ADTH700RMTUW1 | Consult Dimmer Co. | 100-8% | |
| Legrand | CFL/LED | HCL45-3PW | Consult Dimmer Co. | 100-12% | |
| Legrand | U | HCL45-3PW | Consult Dimmer Co. | 100%-16% | |
| Lutron | Triac | AY-600P-WH | Consult Dimmer Co. | 100-12% | |
| Lutron | Triac | D-600P-WH | Consult Dimmer Co. | 100-.1% | |
| Lutron | C*L | DSL06-1LZ | Consult Dimmer Co. | 100-8% | |
| Lutron | Triac | DV-600P | Consult Dimmer Co. | 100-7% | |
| Lutron | C*L | DVCL-153P | Consult Dimmer Co. | 100-1% | |
| Lutron | ELV | DVELV-300P | Consult Dimmer | 100-7% | |
| Lutron | ELV | DVRP-253P | Consult Dimmer Co. | 100-7% | |
| Lutron | Triac | GL-600P-WH | Consult Dimmer Co. | 100-7% | |
| Lutron | ELV | HQRD-6NA | Consult Dimmer Co. | 100-2% | |
| Lutron | Triac | MA-600-WH | Consult Dimmer Co. | 100-5% | |
| Lutron | C*L | MACL-153M | Consult Dimmer Co. | 100-9% | |
| Lutron | ELV | MAELV-600 | Consult Dimmer Co. | 100-2% | |
| Lutron | ELV | NTELV-500 | Consult Dimmer Co. | 100-12% | |
| Lutron | U | PD-5NE-WH | Consult Dimmer Co. | 100-1% | |
| Lutron | CL | PD-6WCL | Consult Dimmer Co. | 100%-1.1% | Drop-out |
| Lutron | ELV | RRD-6NA | Consult Dimmer Co. | 100-2% | |
| Lutron | Triac | S-600P | Consult Dimmer Co. | 100-8% | |
| Lutron | ELV | SELV-300P | Consult Dimmer Co. | 100-7% | |
| Lutron | ELV | TGCL-153P | Consult Dimmer Co. | 100-2% | |

