
44 Harbor Park Drive Port Washington, NY 11050 Tel: (800) 526-2588 Fax: (800) 526-2585

www.waclighting.com

UNDER CABINET XENON LIGHT BAR

MODEL BA-X3



Ordering Matrix				
Model	Series	Finish		
]
BA	X3	BZ	SN	WT

Ordering Example (model - series - finish): BA-X3-BZ

Product Details

Description: Low voltage xenon undercabinet light bar for use on wood cabinets,

desks, shelves and bookcases.

Materials: Extruded aluminum body with an abrasion resistant powder coat

paint finish. Snap-in steel oval lens retention ring(s). Frosted glass

lens. High-low-off switch. Mounting hardware.

Transformer: Integral 120v to 12v electronic transformer.

Connection: The BA-X can be hardwired or use a six foot cord and plug (sold

separately). Knockouts are located on both the backside and on the topside for hardwiring (supplied with one ½" BX/non-metallic sheathed cable adaptor). Poke-home style connectors are pre-installed on the interior wiring for installation convenience.

Lamping: Three xenon 18 watt, 12 volt wedge base lamps included.

Re-lamping is accomplished by removing the snap-on lens/retention

ring. Taking apart the housing is not required.

Finish: BB = Bronze SN = Satin Nickel WT = White

Accessories: BA-IC12/24/36 = Interconnect Cable

BA-PC6 = Power Cord w/grounded plug

Listing: UL & CUL Listed. 5 year W.A.C. Lighting product warranty.

Specification Features

- The BA-X series features a low profile, 11/8", body style.
- The BA-X series has the option of using snap-in interconnect cords to link fixtures together, or using I-Connectors for installing multiple units in a continuous row. One I-Connector is included with each light bar.
- The integral electronic transformer features auto reset, soft start and short circuit protection technologies. The soft start delayed lamp start feature extends lamp life.
- The BA-X can be hard wired to run off a standard wall switch.