
## **EYEBALL** - model: HR-1135

### Low Voltage Miniature Recessed Downlights





# WAC LIGHTING

Responsible Lighting®

Fixture Type:	
Catalog Numbe	r:
Project:	
Location:	

#### **PRODUCT DESCRIPTION**

Low voltage miniature recessed "eyeball" unit with clear glass lens. Used for lighting in cabinets, displays and similar wooden applications. Not intended for use in walls or ceilings.

#### FEATURES

- All steel construction
- Not intended for use in walls or ceilings
- Cutout template included for recessed installations
- Supplied with 36 inch lead wires
- Low profile and shallow installation depth
- Requires a Class 2 transformer
- Order lamp separately
- · Lamp has a 35° adjustable tilt from nadir
- The supplied clear glass lens can be replaced with one lens accessory.
- An all-in-one style recessed unit, comes with housing and trim ready to install out of one box.
- Non-IC unit. Intended for installations where insulating materials will not be present.

#### SPECIFICATIONS

**Materials:** Housing is steel, painted black. Electrical components within the can are a bi-pin ceramic socket with nickel plating and 18 gauge teflon insulated wires with fiberglass sleeves. A total of 30" of insulated wires lead from the socket out the top of the can to the strip-prepared ends.

Transformers: Remote Class 2 Transformer required (order separately).


Light Source: Use one MR11 20W-35W, 12V lamp (order separately).

**Mounting:** 2<sup>5</sup>/<sub>8</sub>" cutout hole. Two horizontal flat springs expand against the cut out hole to hold fixture against the surface. The insulated wires and socket are pre-installed in the housing with the wires leading out through the top of the housing. Simply connect to the remote class II transformer.

Standards: UL & CUL Listed

#### **ORDER NUMBER**

Model #	Finish			
	BK	Black		
HR-1135	СВ	Copper Bronze		
	wт	White		



Example: HR-1135-CB

#### FINISHES



#### **CLASS 2 ENCLOSED ELECTRONIC TRANSFORMERS**

Model	Input	Output	Dimensions
EN-1260-RB2	120V	12V, 1×60W	6½" x 15%" x 1¼"
EN-12120-RB2*		12V, 2 × 60W	6″ x 3¼″ x 25⁄8″
EN-12180-RB2*		12V, 3 × 60W	6¾" x 35%" x 25%"
EN-12300-RB2*		12V, 5 × 60W	8½" x 45%" x 25%"

\*Includes LED indicator lights and integral push in terminals

#### UL LISTED CLASS 2 PLUG-IN ELECTRONIC TRANSFORMERS

EN-1260-P-AR	120V	12V.60W	2¾" x 15%" x 1¾"	BK	Black
	1200	120,0000		WТ	White

**WAC Lighting** www.waclighting.com Phone (800) 526.2588 • Fax (800) 526.2585 Headquarters/Eastern Distribution Center 615 South Street • Garden City, NY 11530 Phone (516) 515.5000 • Fax (516) 515.5050 Western Distribution Center 168 Brea Canyon Road • City of Industry, CA 91789 Phone (800) 526.2588 • Fax (800) 526.2585

WAC Lighting retains the right to modify the design of our products at any time as part of the company's continuous improvement program. MAR 2014