### INSTALLATION INSTRUCTION

## 725 Line Voltage Track Luminaires

HTK-725, LTK-725, JTK-725

# WAC LIGHTING

Responsible Lighting®

#### **CAUTION:**

Read all instructions before installing.

Switch off power before installing or re-lamping.

Do not attempt to energize anything other than a track light fixture.

All installation shall be in accordance with NEC and all local codes

#### **OVERVIEW:**

Fixtures are designed for use on WAC "L", "H", "J" series track. They may also be used on other manufacturer's brand of track (consult factory for compatibility).

#### **LAMPING:**

- 1. Install Lamp. See Specification sheet for compatible lamps.
- 2. Insert lamp into the shade so the lamp pins protrude through the back.
- 3. Place pins in the socket holes and twist 1/4" to the right. The lamp should feel firmly seated.

#### **FIXTURE INSTALLATION**

- 1. Note the track has a groove running it's length to indicate polarity.
- 2. Note the arrow on the locking tab.
- 3. Insert adapter into track slot and rotate it 90 .The arrow should point to the grooved side of the track.
- 4. Make sure the locking tab seats in the track slot.
- 5. Removal is the reverse procedure. Track heads may be positioned anywhere along the track length.

