

# Model: LED-350MA

## LEDme® Button Light Drivers



Fixture Type:

Catalog Number:

Project:

Location:

## Non-Dimming Drivers

### FEATURES

- Magnetic low voltage driver
- Works in *BOTH* series and home-run wiring set ups
- Power up to 4 HR-LED85 fixtures
- Plug and play terminal blocks (for 9W and 12W models)
- Constant current for optimized performance
- Surge protection
- Short circuit protection
- UL 60950 and CUL Listed
- 5 year WAC Lighting product warranty

### ORDER NUMBER and SPECIFICATIONS

	LED-350MA03-RB	LED-350MA09-RB	LED-350MA12-RB
Input Voltage	120VAC, 50/60Hz	120VAC, 50/60Hz	120VAC, 50/60Hz
Input Current	0.1A max	0.15A max	0.2A max
Output Voltage	12VDC	12VDC	12VDC
Output Current	350mA	350mA	350mA
Wattage	3W max	9W max	12W max
Powers up to	1 Button Light	3 Button Lights	4 Button Lights



## Dimming Drivers

### FEATURES

- Magnetic low voltage driver
- May be dimmed with magnetic low voltage (MLV) dimmer
- Works *ONLY* in home-run wiring set up
- Power up to 4 HR-LED85 fixtures
- Plug and play terminal blocks
- Constant current for optimized performance
- Surge protection
- Short circuit protection
- UL 60950 and CUL Listed
- 5 year WAC Lighting product warranty

### ORDER NUMBER and SPECIFICATIONS

	LED-350MA09-DIM-RB	LED-350MA12-DIM-RB
Input Voltage	120VAC, 50/60Hz	120VAC, 50/60Hz
Input Current	0.15A max	0.2A max
Output Voltage	12VDC	12VDC
Output Current	350mA	350mA
Wattage	9W max	12W max
Powers up to	3 Button Lights	4 Button Lights



### WAC Lighting

www.waclighting.com  
Phone (800) 526.2588 • Fax (800) 526.2585

### Headquarters/Eastern Distribution Center

44 Harbor Park Drive • Port Washington, NY 11050  
Phone (516) 515.5000 • Fax (516) 515.5050

### Western Distribution Center

1750 Archibald Avenue • Ontario, CA 91760  
Phone (800) 526.2588 • Fax (800) 526.2585