

# 12V LED/INCANDESCENT PATH & SPREAD

## DOME



**15410 AZT**

## 6" DOME



**15470 AZT, BKT, CBR**

Ordering Guide & Finish	15410 AZT	15470 AZT 15470 BKT 15470 CBR																																								
Housing	Cast Aluminum	Cast Aluminum, Cast Brass																																								
Lamp Base	12V T5 wedge base socket	12V T5 wedge base socket																																								
Supplied Lamp	16.25-W(VA) 921X (17025) Xenon light source Power usage at 12V AC input VA MAX: 16.25-W(VA)	16.25-W(VA) 921X (17025) Xenon light source Power usage at 12V AC input VA MAX: 16.25-W(VA)																																								
Incandescent Lamp Options	11.6-W(VA) 912X (17023) 6.5-W(VA) 918X (17022) 4-W(VA) 901X (17021)	11.6-W(VA) 912X (17023) 6.5-W(VA) 918X (17022) 4-W(VA) 901X (17021)																																								
LED Lamp Options	2W (18039-18041) see page 137. Compares up to 16W Xenon.	2W (18039-18041) see page 137. Compares up to 16W Xenon.																																								
Wiring	30" of usable #18-2, SPT-1-W leads. Cable connectors supplied.	24" of usable #18-2, SPT-1-W leads. Cable connectors supplied.																																								
Mounting Access. (Included)	8" In-ground slotted stake	8" In-ground slotted stake and 18" stem																																								
Optional Accessories	15601 – Surface Mounting Flange 15607 – Surface Mounting Bracket	15601 – Surface Mounting Flange 15607 – Surface Mounting Bracket																																								
Integrated LED Option	15811 – on Page 43	15870 – on Page 42																																								
Notes	Coordinates with our 15310 & 15470 Domed Roof series.	Coordinates with our 15310 & 15410 Domed Roof series. Brass will naturally patina over time.																																								
Photometric with Supplied Lamp	<table border="1"> <thead> <tr> <th>Distance from Light</th> <th>0'</th> <th>1'</th> <th>2'</th> <th>3'</th> <th>4'</th> <th>5'</th> <th>6'</th> <th>7'</th> <th>8'</th> </tr> </thead> <tbody> <tr> <td>Foot Candles</td> <td>22.0</td> <td>9.6</td> <td>4.0</td> <td>1.1</td> <td>.03</td> <td>0.1</td> <td>-</td> <td>-</td> <td>-</td> </tr> </tbody> </table>	Distance from Light	0'	1'	2'	3'	4'	5'	6'	7'	8'	Foot Candles	22.0	9.6	4.0	1.1	.03	0.1	-	-	-	<table border="1"> <thead> <tr> <th>Distance from Light</th> <th>0'</th> <th>1'</th> <th>2'</th> <th>3'</th> <th>4'</th> <th>5'</th> <th>6'</th> <th>7'</th> <th>8'</th> </tr> </thead> <tbody> <tr> <td>Foot Candles</td> <td>6.17</td> <td>4.85</td> <td>4.34</td> <td>2.51</td> <td>1.58</td> <td>1.35</td> <td>0.77</td> <td>0.43</td> <td>0.28</td> </tr> </tbody> </table>	Distance from Light	0'	1'	2'	3'	4'	5'	6'	7'	8'	Foot Candles	6.17	4.85	4.34	2.51	1.58	1.35	0.77	0.43	0.28
Distance from Light	0'	1'	2'	3'	4'	5'	6'	7'	8'																																	
Foot Candles	22.0	9.6	4.0	1.1	.03	0.1	-	-	-																																	
Distance from Light	0'	1'	2'	3'	4'	5'	6'	7'	8'																																	
Foot Candles	6.17	4.85	4.34	2.51	1.58	1.35	0.77	0.43	0.28																																	