

FEATURES & SPECIFICATIONS

INTENDED USE

Provides accent illumination that visually expands the space and creates a relaxing atmosphere in residential and commercial applications such as hospitality, educational, health care and circulation areas. Ideal for use in hallways, stairways, dining areas, foyers, offices and meeting rooms.

ATTRIBUTES

A classic look, this transitionally styled sconce is offered in a hand-dipped, tea-stained glass shade mounted on an antique bronze finished socket housing and matching decorative support arm/canopy or acid-etched, frosted glass shade mounted on a brushed-nickel finished socket housing and matching decorative support, arm/canopy. The shade provides a widespread uniform illumination.

Includes (1) 13W compact full spiral 4-pin 2700K fluorescent lamp for energy efficiency, superior color rendering and long life.

Standard with electronic ballast (120 volt, 60Hz) ensures no flickering and quiet operation without interfering with other electronics.

All mounting hardware included.

LISTING

CUL listed to US and Canadian safety standards and suitable for damp locations. ENERGY STAR® qualified.

WARRANTY


Guaranteed for two years against mechanical defects in manufacture.




Indoor Decorative

Ferros Sconce

Compact Full Spiral Fluorescent








DIMENSIONS

Nominal Size	Lamp Configuration	Model Number	Number of Lamps	(A) Width inches (cm)	(B) Height inches (cm)	(C) Extension* inches (cm)
1 lamp		11531	(1) 13W compact full spiral	4-1/2" (11.4)	9-3/8" (23.8)	6-1/8" (15.6)


^{*} Extension from wall

All dimensions are in inches (centimeters)



ORDERING INFORMATION

Choose the boldface catalog nomenclature that best suits your needs and write it on the appropriate line. Order accessories and replacement parts as separate catalog numbers.



11531 (1) 13W compact full spiral 2700K fluorescent lamp Included

Finish

BZA Antique bronze Brushed nickel Ballast/Voltage **Options**

120 volt residential electronic (blank) ballast (standard)

(Consult factory)

Example: 11531 BZA

Other voltage and ballast types (Consult factory)

Accessories/Replacement parts

CF13S27 R6 **BLST SU13W R12** DFERO TST DFERO WH

13W compact 4-pin full spiral fluorescent lamp³ 13W ballast GU24-pin base socket G24q1 4-pin4 Glass shade, tea-stained Glass shade, opal

- Notes:

 1. INCLUDES (1) 13W compact full spiral 2700K fluorescent lamp.

 2. Use with non-dimmable switches only.

 3. Resale packs must be ordered in increments of 6.

 4. Resale packs must be ordered in increments of 12.

Ferros Sconce

PHOTOMETRICS

Full photometric data report available within 2 weeks from request. Consult factory.



www.lightahome.com