WAC LIGHTING		615 South Street Garden City, NY 11530 Tel:516-515-5000 Fax:516-515-5050 www.waclighting.com	CATALOG NUMBER		TYPE		
SOLORAIL <sup>™</sup> -	SURFACE N	IOUNT TRANSFORME	R	MODEL L	M-EN12-150E		
Ordering Matrix	5		4 <sup>1</sup> /2″	• • • • • • • • *			
Model		Part Numbe	r	Fini	ish		
LM-EN12		150E		DB C	CH BN		
Ordering Example Product Details Description: Catalog Number:	Surface mount Solorail™ syst transformer an LM = Low volta	, enclosed canopy transform	ormer for the WAC ure includes the or.	<ul> <li>Specification Features</li> <li>Dims with electronic low voltage dimmers.</li> <li>Built-in auto reset, soft start, short and overload circuit protection features.</li> </ul>			
Input: Output: Min Load: Max Load:	120V (50/60Hz 12V 35W(dimming) 150W	, ,		<ul> <li>Soft start delayed start feature extends lamp life by limiting abrupt in-rush current to the lamp.</li> </ul>			
Max Input Amp: Mounting:		ndard junction box. Total we M-EN12 configuration match	-	when the insta existing ceiling	an ideal choice allation is on an g.		
Finish: Listing:	Nickel (BN).			<ul> <li>5 year WAC L warranty.</li> </ul>	ighting product		




615 South Street Garden City, NY 11530 Tel:516-515-5000 Fax:516-515-5050 www.waclighting.com

ER MODE		L LM-EN12-250E	
)	PROJECT		
	CATALOG NUMBER	<u>TYPE</u>	

## SOLORAIL™ – SURFACE MOUNT TRANSFORMER





Ordering Matrix							
Model	Part Number	Finish					
LM-EN12	250E	DB	СН	BN			

Ordering Example (model number - part number - finish): LM-EN12-250E-BN

Product Details			Specification Features
Description:	Surface mount electronic low voltage transformer for the WAC Solorail <sup>™</sup> system. The canopy style enclosure includes the transformer and the track power feed adaptor.		Dims with electronic low voltage dimmers.
Catalog Number:	LM = Low voltage Solorail™ EN12 = 12 volt, enclosed canopy transformer 250E = 250 watt electronic		<ul> <li>Built-in auto reset, soft start, short and overload circuit protection features.</li> </ul>
Input:	120V (50/60Hz)		
Output:	12V		Soft start delayed start feature
Min Load: Max Load:	50W (dimming) 1W (non-dimming) 250W		extends lamp life by limiting abrupt in-rush current to the lamp.
Max Input Amp:	2.08A (@ 120V)		The surface mount canopy transformer is an ideal choice
Mounting:	Installs to a standard junction box. Total weight = 2.5 lbs. The standard LM-EN12-250E configuration matches the height of the 4 $\frac{1}{2}$ standoffs (LM-X4).		when the installation is on an existing ceiling.
Finish:	ish: Available in Dark Bronze (DB), Chrome (CH), and Brushed Nickel (BN).		<ul> <li>5 year WAC Lighting product warranty.</li> </ul>
Listing:	UL & CUL Listed.		

WAC Lighting reserves the right to modify the design of our products as part of the company's continuous improvement program.