



# QAP215 • LINA

LOW VOLTAGE MONORAIL  
QUICK ADAPT PENDANTS

Type	
Project	
Catalog No.	



### CATALOG INFORMATION

MODEL	LAMP	MAX WATT	DIMENSIONS	SHADE FINISH	SOCKET FINISH*
QAP 215 LINA	JC Bi-Pin 12V/24V	50W	5-1/8"Ø x 5-3/8"H	BU – Blue RD – Red CHOR – Chrome exterior/Orange interior GMOR – Gun Metal exterior/Orange interior GMWH – Gun Metal exterior/White interior SNOR – Satin Nickel exterior/Orange interior SNWH – Satin Nickel exterior/White interior	CH, SN CH, SN CH GM GM SN SN

\* Socket Finish Key: CH – Chrome, GM – Gun Metal, SN – Satin Nickel

**Ordering Instructions**    **MODEL**    –    **SHADE**    /    **SOCKET**  
**Example:**                    QAP 215    –    BU                    /    CH

### DESCRIPTION

- Clear glass over transparent tinted glass or metal shade. Inner metal shades available in white or orange painted interior.
- Quick Adapt Pendant includes a Quick Adapt Jack, 8' cable, socket assembly, hang-straight tube, protective lamp shield and Halogen JC Bi-Pin 12V 50W lamp. Cable may be field-cut.
- May be used with Jesco Monorail Systems, Standard Track Systems, or with Monopoint/Multipoint Systems – See COMPATIBLE SYSTEMS.
- Compatible fixture: Wall Sconce WS215

**LAMP:**  
Halogen JC Bi-Pin 12V 50W included.  
Optional: 24V lamp, requires appropriate power supply (not supplied).

- SOCKET:**
- For replacement 8' sockets, order QASS13.
  - For high ceiling applications that require a longer socket wire, order QASS13-12. 12' socket sets include a Quick Adapt Jack, 12' cable, socket assembly, hang-straight tube and a JC Bi-Pin 12V 50W lamp. Cable may be field-cut.
  - Sockets offered in the same finish as the inner shade only for CH, SN, GM.

**LISTING:**  
ETL Listed.

### COMPATIBLE SYSTEMS



**MONORAIL SYSTEM**  
The Monorail Fixture Adapter MA-FA (sold separately) provides the connection between the Quick Adapt Pendant to the Monorail.



**STANDARD TRACK SYSTEM**  
The Standard Track Adapter MA-TA-H (sold separately) enables the use of Quick Adapt Pendants in Standard, Line Voltage H-Track Systems. Includes a 50W electronic transformer. Dimmable with an electronic or standard incandescent dimmer.



**MONOPOINT / MULTIPOINT SYSTEM**  
Quick Adapt Pendants may be directly mounted onto Monopoint or Multipoint canopies, which have built-in or remote transformer options.



www.jescolighting.com  
support@jescolighting.com  
**Tech Support:** 855.592.0029

6625 Traffic Ave  
Glendale, NY 11385  
**Main Line:** 800.527.7796  
**Fax Line:** 855.265.5768

219 South 6<sup>th</sup> Ave  
City of Industry, CA 91746  
**Main Line:** 855.654.0110  
**Fax Line:** 626.333.2955

Rev 8  
2/21/2013