



# DIMMER COMPATIBILITY

Project: \_\_\_\_\_

Fixture Type: \_\_\_\_\_

Location: \_\_\_\_\_

Contact/Phone: \_\_\_\_\_

## INCANDESCENT AND MAGNETIC LOW VOLTAGE - FORWARD PHASE DIMMING

Incandescent and Magnetic Low Voltage - Forward Phase Dimming  
 • Dimmable with the use of most forward phase dimmers • Dimming range of 100% down to 10% or lower with a minimum load of one fixture and a maximum load of 50% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.

Example: Fixture Rating = 10W  
 Dimmer Rating = 600W  
 Equivalent Incandescent Load (EIL) Factor = 50% (.5)  
 (600/10) X .5 = 30 Fixtures per Dimmer

### Juno Qualified Dimmers

Fixture Series	Acuity Brands	Lutron®	Leviton®	Cooper®	Legrand®	Belkin®
	Model Numbers:	Model Numbers:	Model Numbers:	Model Numbers:	Model Numbers:	Model Numbers:
Juno Wafer™ LED Downlight Series WF4 SWW5, WF6 SWW6, WF4 REG SWW5, WF6 REG SWW5 and WF8 SWW5	SensorSwitch™ WPD-WH	Diva® LED+ DVCL-153P Caséta® PD-6WCL Series Lutron® Radio RA2® RRD-10ND Maestro® WIRELESS MRF2S-6ND Lutron® Radio RA2® RRD-PRO Maestro® MACL-153MH	IllumaTech™ IPLO6* Series Leviton® SureSlide IPM06-1LZ			

## ELECTRONIC LOW VOLTAGE - REVERSE PHASE DIMMING

Electronic Low Voltage - Reverse Phase Dimming  
 • Dimmable with the use of most electronic low voltage dimmers • Electronic low voltage dimmers require a neutral wire in the wall box • Dimming range of 100% down to 10% or lower with a minimum load of one fixture and a maximum load of 75% of the dimmer rated load (see example); both dimming range and maximum rated load may vary depending on dimmer model.

Example: Fixture Rating = 10W  
 Dimmer Rating = 600W  
 Equivalent Incandescent Load (EIL)  
 Factor = 75% (.75)  
 (600/10) X .75 = 45 Fixtures per  
 Dimmer

### Juno Qualified Dimmers

Fixture Series	Acuity Brands	Lutron®	Leviton®	Cooper®	Legrand®	Belkin®
	Model Numbers:	Model Numbers:	Model Numbers:	Model Numbers:	Model Numbers:	Model Numbers:
Juno Wafer™ LED Downlight Series WF4 SWW5, WF6 SWW6, WF4 REG SWW5, WF6 REG SWW5 and WF8 SWW5		Diva® DVELV-300P Caséta® PD-5NE Series Maestro® MAELV* Series Maestro® MRF2-6ELV* Series				

Consult technical services for additional information regarding other dimmer model qualification.