Kwikset®

NEW CONTEMPORARY INTERCONNECT TRIM

The perfect solution for multi-family housing, Interconnect provides quality, security and style while meeting ADA requirements and fire code ratings.

- Features SmartKey® Re-key Technology with BumpGuard™ Protection

- Lifetime mechanical and finish warranty

- Lever options are in compliance with the American National Standards Institute (ANSI A117.1) and the Americans with Disabilities Act (ADA)

- Meets fire code rating for emergency panic exit

THE #1 SELLING U.S. LOCK BRAND*

97499-KW

Interconnect Specifications

Door Prep	2 $\frac{1}{8}$" diameter face hole & 1" diameter latch hole
Backset	Adjustable 2 $\frac{3}{8}$" or 2 $\frac{3}{4}$"
Door Thickness	1 $\frac{3}{8}$" – 1 $\frac{3}{4}$" automatic adjustment
Cylinder	• 506 and 508 utilize 6-pin or SmartKey on 780 deadbolt • 505 utilize 5-pin on 660 deadbolt • 502 - determined by handleset ordered
Faceplates	1" x 2 $\frac{1}{4}$" round corner standard

Strikes	Deadbolt Strike: UL 5278, 3223 (WFL 4632 opt.).
Door Handing	506, 508, 505, 507 - reversible 502 - specify handing.
ANSI/ BHMA	• 506, 508, 505 - Grade 3 Certified • 502 - Determined by handleset ordered.
ADA	Lever options are in compliance with the American National Standards Institute (ANSI A117.1) and the Americans with Disabilities Act (ADA)
UL	Meets 3 hour fire rating.

Interconnect Dimensions

Dimensions	A	B	C	D
Interior	1 $\frac{13}{32}$"	2 $\frac{1}{16}$"	5 $\frac{3}{8}$"	1 $\frac{29}{32}$"
Exterior	2 $\frac{27}{32}$"	9 $\frac{3}{16}$"		

Finishes

11P
Venetian
Bronze

15
Satin
Nickel

**26**
Polished
Chrome

26D
Satin
Chrome

Re-key in seconds.

1 Insert functioning key & turn 1/4 turn clockwise.

2 Insert & remove the SmartKey learn tool. Remove functioning key.

3 Insert new key & turn 1/2 turn counter-clockwise. Done. *Your lock is now re-keyed!*

SMARTKEY™
RE-KEY TECHNOLOGY