

INSTALLATION INSTRUCTIONS

FOR MADISON INVERTED PENDANT 178063

Meyda
CUSTOM LIGHTING

CAUTION: FAILURE TO INSTALL THIS FIXTURE PROPERLY MAY RESULT IN SERIOUS PERSONAL INJURY OR DEATH AND PROPERTY DAMAGE. We recommend installation by a licensed electrician. This product must be installed in accordance with applicable installation code(s), by a person familiar with the construction and operation of the product and the hazards involved.*

Caution: Do not exceed maximum wattage noted on fixture. Use only recommended bulbs with fixture.

FIXTURE COMPONENTS

1. 178575 36"W x 10.5"H Randsburg Rock Idalight Bowl
2. Hub with attached 8 LT Cluster and 60"Wire
3. Canopy Assembly
4. 48" Chain
5. Finial Assembly
6. Loop Assembly (QTY 6) for Idalight Bowl
7. Arms (QTY 6)

Caution: Be sure power is off at the main breaker box prior to installation. Read all instructions in their entirety before beginning installation.

1. Carefully unpack all components and make certain that everything is accounted for.
2. Remove screw collar(D) from loop(E) and slide up through canopy crossbar(A), threaded rod(B), and loop(E) with quick link(F).
3. Attach crossbar(A), threaded rod(B), and loop(E) with quick link(F) to J-Box in ceiling, ensuring that electrical supply wires remain accesible.
4. Connect desired length of chain(G) to quick link(H) attached to loop(I) on hub(J).
5. Slide screw collar(D) and then canopy(C) over chain(G) and let rest on top of hub(J).
6. Secure chain(G) with connected hub(J) to quick link(F) attached to loop(E) on J-Box.
7. Run wire from hub(J) through every 3rd link of chain.
8. Feed wire through loop(E) and threaded rod(B) attached to J-Box. Pull all excess wire out of J-Box and make connection to electrical supply wires following local codes.
9. Following succesful connection of fixture to power, slide canopy(C) and screw collar(D) up chain(G) to ceiling. Screw collar(D) onto exposed threaded rod(B) until tight.
10. Using Diagram A, attach finial assembly to bottom hole in Idalight Bowl.
11. Using Diagram B, attach loops to holes on Idalight Bowl.
11. Attach arms to hooks on hub and other end to loops on Idalight Bowl.
12. Install 8 Med Base 40Watt Bulbs(not included) into sockets.

