

# ARCH

Wall mount • Damp location listed

## Specifications:

### P2063-0930K9

#### Description:

Arch LED is an innovative series of acrylic LED wall sconces that optimizes aesthetic appeal. Three-light LED bath with AC LED module. Screen-printed lens accessories - in fabric linen or nature-inspired patterns - can be inserted into the fixtures for a unique effect. A perforated metal mesh end cap diffuses light above and below the fixture to provide even illumination.

#### Images:



#### Construction:

- Brushed Nickel (-09) (plated)
- White acrylic diffusers
- LED Module is replaceable (part # 93053641)
- Flicker-free dimming to 10% brightness with most ELV type dimmers (See Dimming Notes)
- Title 24 compliant
- Back plate covers a standard 4" hexagonal recessed outlet box
- Mounting strap for outlet box included
- Six inches of wire supplied

#### Performance:

Number of Modules	3
Input Power	17W
Input Voltage	120V
Input Frequency	60Hz
Lumens/LPW	1,211/71.2 (LM-79) per module
CCT	3000K
CRI	90
Life	60,000 (L70/TM-21)
EMI/RFI	FCC Title 47, Part 15, Class B
Min. Start Temp	-30° C
Max. Operating Temp	30° C
Warranty	5 year warranty
Labels	cCSAus Damp location listed ENERGY STAR® qualified

#### Dimensions:

Width: 21-3/4"  
 Height: 6"  
 Depth: 3"  
 H/CTR: 3"

#### Catalog number:

Base	Finish	Color Temp	CRI
<b>P2063</b>	<b>09 - Brushed Nickel</b>	<b>30K - 3000K</b>	<b>9 - 90 CRI</b>

**P2063-0930K9****Dimming Notes:**

P2063 is designed to be compatible with many Electronic Low Voltage (ELV-Reverse Phase) controls.

The following is a partial list of known compatible dimmer controls:

**Electronic Low Voltage ELV Reverse Phase Controls**

Lutron	Diva Series	(Part Number DVELV-300P)
Lutron	Nova T Series	(Part Number NTELV-300)
Lutron	Vierti Series	(Part Number VTELV-600)
Lutron		(Part Number MAELV-600)
Lutron		(Part Number SPELV-600)
Leviton		(Part Number AWRMG-EAW)
Leviton		(Part Number 6615-P)

Digital type dimmers are not recommended.

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation.

Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.