Mini Echo Pendant



Translucent cylinder over a white case glass cylinder, highlighted with three metal details. Includes low-voltage, 50 watt halogen bi-pin lamp or 8 watt, 300 delivered lumen, 3000K, replaceable SORAA® LED module and six feet of field-cuttable cable. Dimmable with low-voltage electronic or magnetic dimmer (based on the transformer) Works with SORAA.

INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system.

ACCESSORIES & OPTICAL CONTROLS

SORAA® LED Bi-Pin Replacement Pendant Module, Swag Hook















smoke

ORDERING INFORMATION

700 SYSTEM ECP COLOR FINISH LAMP FREEJACK Z ANTIQUE BRONZE 12 VOLT HALOGEN A AMBER -LEDS830 12 VOLT LED 80 CRI 3000K -24 24 VOLT HALOGEN MONOPOINT C CHROME **Q** AQUAMARINE S SATIN NICKEL C CLEAR MO2 TWO-CIRCUIT MONORAIL S SMOKE

Note: MP includes 4" Round Flush Canopy. Note: MP includes 4 Round Flush Canopy.

U STEEL BLUE


Chrome not offered on Monorail & Two~Circuit Monorail.



Skokie, Illinois 60077

T 847.410.4400 F 847.410.4500

Tech Lighting, L.L.C.



178 mm

4"

102 mm



©2017 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.