

LOW-VOLTAGE PENDANTS

Cone Pendant



DESCRIPTION

Case glass cone with reflective white interior or transparent glass cone. Case glass includes low-voltage, 50 watt halogen bi-pin lamp or 6 watt replaceable LED module. Transparent glass includes low-voltage, 50 watt MR16 flood lamp. Each include six feet of field-cuttable suspension cable.

INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system. For use on T~TRAK, order FreeJack version and T~TRAK FreeJack Connector (sold separately).

ACCESSORIES & OPTICAL CONTROLS

Swag Hook

WEIGHT

1.35lb / 0.61kg ±

COLOR OPTIONS



amber



clear



cobalt




red



white



cobalt



ORDERING INFORMATION

700	SYSTEM	CON	COLOR	FINISH	LAMP
FJ	FREEJACK		A AMBER	Z ANTIQUE BRONZE	12 VOLT HALOGEN
K	KABLE LITE		C CLEAR	C CHROME	-LED 12 VOLT LED 3000K
MO	MONORAIL		P COBALT	S SATIN NICKEL	-24 24 VOLT HALOGEN
MO2	TWO-CIRCUIT MONORAIL		R RED		
			W WHITE		

Note: LED option not available on MO2 at this time.

Antique Bronze is not available for Kable Lite.



TECH LIGHTING®

7400 Linder Avenue
Skokie, Illinois 60077

T 847.410.4400
F 847.410.4500

Tech Lighting, L.L.C.

700 ____ CON _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____



©2013 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.