

Kable Lite Surface Transformer-150W Mag**DESCRIPTION**

This single-feed surface transformer converts standard 120 volt line-voltage to 12 volts to provide the necessary voltage for powering a Kable Lite system. It can power lamps totaling up to 150 watts. The transformer is concealed inside a decorative housing with a fast-acting secondary circuit breaker that will safely turn off the system should a short occur. Once the short has been removed the breaker can be reset.

INSTALLATION

This product can mount to either a 4" square electrical box with round plaster ring or an octagon electrical box (not included).

DIMMING

Dimmable with a 600 watt low-voltage magnetic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics). This surface transformer includes a preinstalled debuzzing dimming coil to reduce audible noise when using a low-voltage dimmer.

OTHER INFORMATION


The shortest rigid standoff that can be used with this surface transformer is the 2.5" rigid post standoff (sold separately). This surface transformer may be plugged in with the addition of a Plug Option, a 16' cord with plug (sold separately). 12 volt transformers require the use of 12 volt lamps.

WEIGHT

7.2lb / 3.27kg

ORDERING INFORMATION**700SRT15D FINISH**

Z ANTIQUE BRONZE
B BLACK
C CHROME
S SATIN NICKEL
W WHITE



TECH LIGHTING®

7400 Linder Avenue
 Skokie, Illinois 60077

T 847.410.4400
 F 847.410.4500

www.techlighting.com

700SRT15D _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____



©2011 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.