

FreeJack 4" Square Flush Canopy



DESCRIPTION

Mounts to a standard 4" junction box with round plaster ring (provided by electrician). Electronic transformer (included) fits in junction box. One FreeJack port; for ceiling or wall.

INSTALLATION

This product can mount to either a 4" square electrical box with round plaster ring or an octagonal electrical box (not included). Transformer (included) fits in junction box. For ceiling or wall. If wall mounting, head should be no longer than 6".

DIMMING

120V IN/12V OUT and 120V IN/24V OUT dimmable with a standard incandescent dimmer (not included). 120V LED dimmable with a low-voltage electronic dimmer (not included). 277V LED dimmable with a 277V low-voltage electronic dimmer (not included). 277V IN/12V OUT dimmable with a 277V incandescent dimmer (not included).


OTHER INFORMATION

For use with any 12 or 24 volt halogen or 12 volt LED FreeJack pendant or head (sold separately).

WEIGHT

0.8lb / 0.36kg

ORDERING INFORMATION



700FJ4SQ FINISH	VOLTAGE
Z ANTIQUE BRONZE	120V IN/12V OUT
B BLACK	024 120V IN/24V OUT
C CHROME	277 277V IN/12V OUT
S SATIN NICKEL	
W WHITE	



TECH LIGHTING®

7400 Linder Avenue T 847.410.4400
Skokie, Illinois 60077 F 847.410.4500

www.techlighting.com

700FJ4SQ _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____

