
MONORAIL

MonoRail Remodel Recessed Transformer-300W Electronic





DESCRIPTION

This single-feed remodel recessed transformer converts standard 120 line-voltage to 12 volts to provide the necessary voltage for powering a MonoRail low-voltage lighting system. It can power lamps totaling up to 300 watts. The transformer installs in similar fashion as a remodel recessed downlight and is concealed inside a housing that recesses above the ceiling. The decorative housing is the only visible portion of the transformer once installed. Should a short occur a fast acting secondary circuit breaker that will safely turn the system off. Once the short has been removed the unit can be reset by simply flipping the wall switch off and back on. Dimmable with a 600 watt low-voltage electronic dimmer.

INSTALLATION

In remodel applications, install the Remodel Recessed Transformer in close proximity to an existing junction box, drill through the finished ceiling in the location where the Remodel Recessed Transformer will be installed, and cover the existing junction box with a thin, field-paintable metal cover (included) as the NEC requires. In new construction, bring power to the Remodel Recessed Transformer directly. Insulation must be kept at least 3" from the transformer and housing (non-IC).

DIMMING

Dimmable with a 600 watt low-voltage electronic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics).

OTHER INFORMATION

White finish has satin nickel feed. The shortest rigid standoff that can be used with this surface transformer is the 2" rigid standoff (sold separately). If dropping the rail more than 2" below the ceiling, order the desired rigid standoff length and one compatible power extender (sold separately). 12 volt transformers require the use of 12 volt lamps.

WEIGHT

2.02lb / 0.92kg

ORDERING INFORMATION

700MOSRR30E FINISH

Z ANTIQUE BRONZE C CHROME S SATIN NICKEL W WHITE

700MOSRR30E _____

FIXTURE TYPE:

JOB NAME:

NOTES:



www.techlighting.com



©2011 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.