

F R E E J A C K


FreeJack 4" Square Flush Canopy LED

**DESCRIPTION**  
Mounts to a standard 4" junction box with round plaster ring (provided by electrician). Electronic transformer (included) fits in junction box. One FreeJack port; for ceiling or wall.

**INSTALLATION**  
This product can mount to either a 4" square electrical box with round plaster ring or an octagonal electrical box (not included). Transformer (included) fits in junction box. For ceiling or wall. If wall mounting, head should be no longer than 6".

**OTHER**  
For use with any 12 volt LED FreeJack pendant or head (sold separately)

**WEIGHT**  
0.8lb / 0.36kg ±



ORDERING INFORMATION

700FJ4SQ FINISH	VOLTAGE
<b>Z</b> ANTIQUE BRONZE	<b>-LED</b> 120V IN/12V OUT LED
<b>B</b> BLACK	<b>-</b> 277V IN/12V OUT LED
<b>C</b> CHROME	<b>LED277</b>
<b>S</b> SATIN NICKEL	
<b>W</b> WHITE	



TECH LIGHTING®

7400 Linder Avenue T 847.410.4400  
Skokie, Illinois 60077 F 847.410.4500

Tech Lighting, L.L.C.

700FJ4SQ \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_



©2013 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C.  
Tech Lighting reserves the right to change specifications for product improvements without notification.