LOOM 14 FLUSH SQUARE

TECH LIGHTING

PRODUCT FEATURES

- · Mid-century modern design featuring asymmetrical look
- · Available in a Black/Gold finish
- Fully dimmable integrated LED light source
- · Ideal for bathroom lighting, hallway lighting and bedroom lighting
- The LED Driver is housed within the junction box for this product
- 1 year warranty with no lamping option. 5 year warranty with LED lamping option, visit techlighting.com 'About Us' for more warranty details



LAMPING

LED includes 20 watt 783 delivered lumens 90 CRI 3000K LED module. Dimmable with a low-voltage electronic dimmer. 120v or 277v

Satin Gold/Matte Black



Satin Gold/Matte Black

ORDERING INFORMATION

700FMLMO FINISH	LAMP	
BG BLACK/GOLD	-LED930 LED 90 CRI 3000K 120V	
	-LED930-277 LED 90 CRI 3000K 277V	

700FMLMO
JOB NAME
NOTES




LOOM 14 FLUSH SQUARE

TECH LIGHTING

SPECIFICATIONS

HARDWARE MATERIAL	Metal
SHADE MATERIAL	Steel
NET WEIGHT	10 lbs
HEIGHT	3.5in
WIDTH	14in
LENGTH	14in
UP LIGHT / DOWN LIGHT / BOTH?	
WET LISTED	
DAMP LISTED	Yes
DRY LISTED	
WALL / CEILING MOUNT	
GENERAL LISTING	ETL Listed
INCLUDES	



LAMPING SPECIFICATIONS

	LED LAMP	INTEGRATED LED	NON LED	NO LAMP
DELIVERED LUMENS		783		
WATTS		20		
MAX WATTAGE PER BULB		20W		
INPUT VOLTAGE		120V		
		277V		
DIMMING TYPE*		ELV, TRIAC		
		0-10V		
ССТ		3000K		
CRI		90 CRI		
LED LIFETIME				
L70		>50000		
AVERAGE BULB HOURS				
FIELD SERVICEABLE LED				
LAMP BASE		Integrated LED		
LAMP SHAPE		Integrated LED		
LAMP INCLUDED?		True		
WARRANTY**		5 Years		

^{*} Dimming information available at www.techlighting.com/Downloads#dimming
** Visit techlighting.com for specific warranty limitations and details.

T20/T24/JA8 INFORMATION

	Integrated LED	Replacement LED Lamp	No Lamp *
This product can be used to comply with California Building Energy Efficiency Standards 2016 Title 24 Part 6 / JA8.	Yes		
This product can be used to comply with California Appliance Efficiency Standards 2016 Title 20 and may be shipped to and sold in California.	N/A		

^{*}If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.

